



# A80S Smart Wake-Up Light User Manual

Please read this manual thoroughly before using and keep it for future use.

## WARNING

To reduce the risk of Fire, Electric Shock, or Injury to Persons:

- 1. This appliance is only intended for household use, including similar use in hotels.
- 2. Place this appliance on a stable, level and non-slippery surface.
- 3. Do not use this appliance in wet surroundings (e.g. in the bathroom or near a shower or swimming pool.)
- 4. Make sure the adapter does not get wet.
- 5. Do not let water run into the appliance or spill water onto the appliance.
- 6. Only use the original adapter. Do not use the other adapter if they are damaged.
- 7. This appliance has no on/off switch. To disconnect the appliance from the power source, remove the the plug from the wall outlet.
- 8. Do not use this appliance as a means to reduce your hours of sleep. The purpose of this appliance is to help you wake up more easily. It does not diminish your need for sleep.

## **STORAGE**

- 1.Clean the appliance with a soft cloth.
- 2. Do not use abrasive cleaning agents, pads or cleaning solvents like alcohol, acetone, etc., as this might damage the surface of the appliance.
- 3. If the appliance will not be used for an extended period of time, remove the power cord from the wall outlet and store the appliance in a safe, dry surroundings where it will not be crushed, banged, or subject to damage.


# **OVERVIEW**



- 1) Alarm Clock 2
- (2) Alarm Clock 1
- (3) Down Button
- (4) LED Light
- (5) Up Button
- (3) op Batton
- 6 Snooze Button
- (7) Volume +
- (8) Radio

- 9 Volume -
- (10) Sleep Timer
- (11) Setting Button
- (12) USB Output
- (13) Antenna
- (14) Micro USB Input
- (15) Speaker
- (16) Button Battery






# **OPERATION GUIDE**


#### First use- setting the clock time:

You have to set the clock time when you plug in the appliance for the first time.

## Set the time



Plug in the power and start setting.



Hold for 3 seconds until the hour time begins to blink.




Use  $\bigcirc$  to adjust the hour.



Press the again to confirm the hour time and move to the minutes.



Use ••• to adjust the minutes.



Press the once more to confirm the minutes and move to choose the time format.

**Note:** When the 12-hour time format is selected, PM or AM will be displayed.

# Setting Alarm Clock

You can set four alarm clocks for this wake-up light. (Note: clock 3 & clock 4 can only be set on APP) Take clock 1 setting as an example:





1.In time state, press (1) to turn on alarm, the alarm symbol appears on the display when you turn on it, and disappears when you turn off the alarm.


2.Hold  $\begin{tabular}{l} \begin{tabular}{l} \beg$ 






3.Press 👸 second time to confirm the hour time and move to the minutes, and use 🕩 🗀 to adjust the minutes.

4.Press 📆 third time to confirm the minutes and move to choose the alarm sound, and use 🕩 🗀 to adjust your choices. (You can choose between 7 pre-set sounds or FM radio as a wake-up sound.)





5.Press (†) fourth time to confirm the alarm sound and move to set the wake-up sound volume, and press (+• -) to adjust the volume

**Note:** When the set light time arrives, the light will slowly turn from dark to the preset brightness level. **OFF** means turning off the light. Set the light state to **OFF** when you do not need a light to wake up



7.Press (1) sixth time to confirm the light brightness and move to set the simulated sunrise time. and press (1) to adjust from 10-60 MIN, then press the (1) to confirm, finish setting.

(You can set the light to turn on 10-60 minutes before the alarm sounds. In the set sunrise simulation time the light intensity of the lamp gradually increases to the set level and the light color changes from deep morning red to bright daylight.)

Leave for about 15 seconds to confirm selected option.

# **SNOOZING**



When alarm clock goes off, press  $\ \textcircled{\ \ }$  to enter snooze state, you can get an extra 9 minutes of sleep time.

(Note: snooze up to 5 times.)

\*When alarm clock goes off (or snooze state), press the corresponding alarm clock button to turn off light and sound.

\*When alarm clock goes off, if there aren't any operations within 15 minutes, it will trun off light and sound automatically.

# SWITCHING THE LIGHT ON/OFF

# You can adjust the display type: Sunrise Light OR Colorful Light

## Sunrise Light:



Press to turn on/turn off sunrise light



Press (+) -) to adjust the light intensity

## Colorful Lights:

Double click 🛞 to turn on/turn off colorful lights, and enter automatic mode;

Press 🛨 🕒 to switch manual mode.

Long press (+) -) to switch to automatic mode again.

# SWITCHING THE FM RADIO ON/OFF

Press ® for 3 seconds to turn on automatic search mode in your first use, the radio will automatically scan radio frequencies and save the frequency of P01, P02....





#### Turn on radio


In time state, press (a) to switch on/switch off FM radio, Long press (4+ / 4- for three seconds to set FM frequency. Short press (4+ / 4- to set radio volume.

#### Turn off radio


In radio-on state, press (a) to turn off FM radio.

Note: To get a good radio signal, fully unwind antenna and move it around until you receive the best reception.


# SETTING THE SLEEP TIMER



Press 🏵 to initate sleep timer



Long press to set the simulated sunset time, and press to adjust the timer.



Press second time to set the sleeping light, and press to adjust the light intensity.



Press third time to set the sleeping music, and press to choose the sound. You can use the natural sounds or the FM radio as a sleeping sound, the wake-up light has three buit-in natural sounds.



Press Prourth time to set the sleeping sound volume, and press For adjust the volume.

**Note:** After finish setting, the light will slowly turn form the preset brightness level to dark, and the light will turn off at the end of the preset time.

Leave for about 15 seconds to confirm selected option.

# CONNECTING YOUR MOBILE DEVICE

 Download Smart Life into your mobile device from App Store/ Google Play or by scanning QR code. • Download 'Smart Life' / Scan for Video Instruction





Android/IOS

Scan for Video Instruction

2. Create an Account and Log in





#### 3. Add Device & Connect WIFI







Power on the light and confirm Wi-Fi blinks rapidly



Turn the device on and long press the Snooze button (about 10 seconds) until the Wi-Fi icon begins to flash rapidly.



Select your own Wi-Fi and enter correct password




Wait for connecting



Create a name for your wake-up light.

# 4. How to Operate the Light via Smart Life

## **APP Operation Panel**



A. Click • to set the time of the wake-up light and time display brightness.




Please make sure you have chose the Network auto-time, otherwise alarm settings might not inaccurate. B. Click  $\ref{13}$  /  $\ref{23}$  to set the four alarm clocks.





# 4. How to Operate the Light via Smart Life

## **APP Operation Panel**



A. Click • to set the time of the wake-up light and time display brightness.



Please make sure you have chose the Network auto-time, otherwise alarm settings might not inaccurate. B. Click  $\ref{13}$  /  $\ref{23}$  to set the four alarm clocks.





## HOW TO CONNECT WITH AMAZON ALEXA

1.Download Amazon Alexa and sign in your Amazon account.




2. — Select Skills & Games, search Smart Life, and ENABLE TO USE it.







—Login your "Smart Life" account, then **Authorize** and close the **successfully linked** page after it is connected successfully to enter **Discover Devices** page.







#### 3. Discover Devices

This wake-up light works with Alexa, through this skill, Amazon Alexa will find and list devices you originally added in Smart Life App.







#### Note:

If your Smart Life account has linked to Alexa, please add the devices by the following steps:















# HOW TO CONNECT WITH GOOGLE HOME


1.Download Google Home and sign in your google account.















2. Login your "Smart Life" account, then **Authorize** and close the **Accounts now linked** page after it is connected successfully to enter **Choose Device** page. Then you can control the wake-up light via Google Home after complete setting.











## TROUBLE SHOOTING

This part summarizes the most common problems you could encounter with the **Wake-Up Light**. If you are unable to solve the problem with the information below, please feel free to contact **support@heimvision.com** for assistance.

#### Q1. The appliance does not work at all.

- \* Perhaps the adapter is not inserted properly in the wall outlet. Plug the adapter properly in the wall outlet.
- \* Perhaps there is a power failure. Check if the power supply works by connecting another appliance.

#### Q2. What should I do when I cannot link the Wake-Up Light with the Smart Life App?

- \* Check if the Wake-Up Light is powered on;
- \* Make sure your mobile device is connected to the 2.4GHz Wi-Fi Network;
- \* Make sure the password of your Wi-Fi network entered in **Smart Life App** is correct when linking **Wake-Up Light**;
- \* Make sure the **Wake-Up Light** is ready for linking: the Wi-Fi indicator flashes quickly. If not, please press the Snooze button (about 10 seconds) until the Wi-Fi indicator begins to flashes rapidly.
- Q3. Why did I fail to set the alarm clock to ring only on weekdays?
  - \* Please turn on the **Network auto-time** in the setting interface of **Smart Life App**, then you can set the alarm clock according to your needs.

#### Q4. The radio produces a crackling sound.

- \* Perhaps the broadcast signal is weak, please fully unwind antenna and move it around until you receive the best reception.
- Q5. How can I set the alarm 3 and alarm 4?
  - \* Alarm 3 & Alarm 4 can only be set on **Smart Life App**.

#### Q6. Could I completely turn off the time display?

\* Yes, you could turn it off in the setting interface on **Smart Life App**.

#### Q7. The light wakes up me too early.

- \* Perhaps the light intensity level you set is not appropriate for you. You can try a lower light level.
- \* Move the Wake-Up Light further away from the bed.

#### Q8. The light wakes up me too late.

- \* You can try to set at a higher light intensity level.
- \* Make sure the **Wake-Up Light** is located at a height at which the light is not blocked by your bed, comforter, pillow or any other things.

## WARRANTY

### 30-Day Money-Back Guarantee for Any Reason

You may return your product within 30 days of purchase to receive a FULL REFUND for any reason. But if the reason for return isn't quality-related, the customer must pay for the return shipping.

## 24-Month Warranty for Quality-Related Issues

HeimVision warrants its products to be free from defects in material and workmanship, under normal use, during the warranty period. Within 24 months, HeimVision will provide a replacement and cover any return shipping costs for products that fail in normal use.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) this device may not cause harmful interference, and
- (2)this device must accept any interference received, including interference that may cause undesired operation.



# **CUSTOMER SUPPORT**

North America support@heimvision.com
United Kingdom support.uk@heimvision.com
Deutschland support.de@heimvision.com
Italia support.it@heimvision.com