ATTENTION ILINK FOR CARPLAY USERS: FIRMWARE VERSION 1.3.0 IS REQUIRED FOR FUNCTIONALITY OF THE ILINK

DYNAVIN N6 FIRMWARE UPDATE INSTRUCTIONS- VERSION 1.3.0

Dynavin N6 firmware updates are available on Dynavin's website <u>www.dynavin.com</u>. To check your current firmware version, swipe left and select the "Info" icon on the Dynavin's main menu. Look at the number on the first line.

1) At <u>www.dynavin.com</u>, go to the bottom of the page and click the link "Dynos 1.3.0 is available to download now!" as shown below.

Recent News	> Dynos 1.3.0 is available to download now!
@ Copyright 2014 DY	IAVIN. All rights reserved. Reproduction in whole or in

2) Follow the link provided on step 1 of the PDF instructions page to access the firmware software via Drobox as shown below.

Update to Dynos 1.3.0 Note: the Software can not suitable for N6-A5

1.Download the file from the link below https://www.dropbox.com/s/rohelg6njj0na8r/1229_1.3.0.rar?dl=0

- Click download. (You do not need to create a Dropbox account to download.) The files download will be a .rar compressed file. If you do not have a utility capable of extracting .rar files, you will need to get one. We use a free utility called <u>"RAR Extract Frog" http://download.cnet.com/Free-RAR-Extract-Frog/3000-2250_4-10804840.html.</u>
- 4) Once the firmware file has downloaded, right click the file and select "Open With" > "Choose another app" > RAR Extract Frog. OR, upload the file within the app RAR Extract Frog.
- 5) You should now see 4 files extracted (as shown in PDF instructions in Step 3). Copy or drag the files onto a micro SD card. **DO NOT PUT THE FILES IN A FOLDER.** (Depending on your computer, you may need an SD card adapter in order to insert it into your computer.)
- 6) Once the <u>extracted</u> files are on it, insert the micro SD card into the "MMC" slot of your Dynavin, swipe left to "Info". (Hint: If the firmware on your card is good and ready to be downloaded, there will be a tiny green light within the "Update Now" button on the screen.)
- 7) Select "Update Now". It will install and reboot within about 2-3 minutes.
- 8) Confirm that the update installed properly by swiping left to "Info" on the main screen and checking that it says **DynOS 1.3.0** on the first line.

If you need help, feel free to contact us at J&T Distributing 559.486.4047 8:30AM-4PM PST or email <u>support@jandtdistributing.com</u>.

Thank you!