



F-1 Fazer

Antari's most famous and popular Fazer X-310 (X-310II and X-310PRO) has been sold around the globe for 10 years! Over the past 10 years almost 80,000 machines working diligently on the stage with numerous digital lights!

Now it is time for X-310 to take a bow. The F-1 with major modern technology features not only X-310 strengths in its overall design but modifies its functions from what we have learned from and listened to the needs from users, experts and the markets. This time we have added air pump to enhance and smooth the mixture of fog liquid and air, plus a more strong output pipe with self-cleaning feature to ensure huge output volumes yet without worrying of clogging.

F-1 also has a smart function to automatically identify right frequency while there are more than one frequencies being used in a country.

If you have been using X-310, you will like F-1 even more!

If you have not used X-310 before, then this is the best time to give brand new F-1 a shot to enhance the whole pigments of lighting colors on stage!



FEATURES

1. 3 DMX Control Mode
 - a. Fog volume with fan at 100%
 - b. Fog and Fan volume control
 - c. Fog and Fan sync mode
2. Larger tube diameter
3. Built-in air pump with self cleaning function
4. The stability in all details while the maturity reaches perfection
5. Highest fog quality: dry and pure

SPECIFICATIONS

Input Voltage	US Version AC120V 50/60Hz 6.8A EU Version AC230V 50/60Hz 3.5A
Rated Power	760W
Warm-up Time	4.5 mins (approx.)
Fluid Consumption	8.5 ml/ min (100% output)
Fluid tank capacity	2.4 liters
Compatible fluid	Antari FLG Heavy fog fluid
Operating time	4.5 hrs at max. output
Ambient temp. range	0°C-40°C (32°F-104°F)
Control	DMX512, Timer, Manual, Wireless (Optional), W-DMX (Optional)
DMX Channels	2 Channels
Connection	Neutrik Powercon (Power) XLR 3-pin and 5-pin (DMX)
Optional Accessories	W-DMX-PCBR Wireless DMX WTR-10 Wireless Remote Set WTR-40 Wireless DMX and W-1 Transmitter
Dimension	L618 W275 H327 mm (L24.33 W10.83 H12.87 inch)
Weight	14.1 kg (31.09 lbs)



www.antari.com