

**HZ-1000 takes just one, flow quietly...
The rest remains on the stage suddenly becomes
the center of the focus. All eyes on it!!**

It's a little big, a little heavy but HZ-1000 really user friendly!

The haze it creates are thin and even, spread quickly and easily, dry, and quiet... even the weakest lighting make it shine bright!!

1. The maximum haze output is HZ-500's double. Two operational modes: Single-Compressor or Twin-Compressor mode can be selected to create needed haze volume.
2. Equipped with TFT color Touch Panel provides simple control interface.
3. Flight case with wheels gives better protections for tours.
4. Internal turbo fan enables haze to go higher and farther. Wind diverter can be set to 2 different angles.
5. Dry haze with minimum residues.
6. Large reservoir allows long time operation without frequent refills.
7. Clear liquid level indication window.
8. Both 3-pin and 5-pin DMX ports are available.



SPECIFICATIONS

Voltage	AC 100-120V, 50/60Hz 9.6A AC 220-240V, 50/60Hz 4.8A
Power Consumption	1150W
Fluid Consumption Rate	2.2 ml / per min (100% output)
Tank Capacity	6.4 Liters
Compatible fluid	Antari HZL Haze Fluid
Operating Time	40 hrs at max. output
Ambient temp. range	0 °C - 40 °C (32 °F-104 °F)
Control Options	DMX 512, Manual, Timer, W-DMX(Optional)
DMX Channels	2 Channels
Connection	Neutrik Powercon True1 (Power) XLR 3-pin and 5-pin (DMX)
Optional accessories	W-DMX-PCBR Wireless DMX 512
Dimension	L 690 x W510 x H 610 mm (L 27.16 x W 20.07 x H 24.01 inch)
Weight	74.6 kg (164.46 lbs)