

MF-1 Mainframe Connector Pinouts - w/ MX-1

<b>Connector</b>	<b>Frame Position</b>	<b>Pin (+Red)</b>	<b>Pin (-Blk)</b>	<b>Pin (Shld)</b>
J-1 (Inputs)	1	1	18	34
J-1	2	2	19	35
J-1	3	3	20	36
J-1	4	4	21	37
J-1	5	5	22	38
J-1	6	6	23	39
J-1	7	7	24	40
J-1	8	8	25	41
J-1	9	9	26	42
J-1	10	10	27	43
J-1	11	11	28	44
J-1	12	12	29	45
J-1	13	13	30	46
J-1	14	14	31	47
J-1	15	15	32	48
J-1	16 (Not Used)	16	33	49
		17,50 Not Used		
<b>Connector</b>	<b>Frame Position</b>	<b>Pin (+)</b>	<b>Pin (-)</b>	<b>Pin (Shld)</b>
P-A (Outputs)	1	1	3	2
P-A	2	4	6	5
P-A	3	7	9	8
P-A	4	10	12	11
P-A	5	13	15	14
P-A	6	16	18	17
P-A	7	19	21	20
P-A	8	22	24	23
P-A	9	25	27	26
P-A	10	28	30	29
P-A	11	31	33	32
P-A	12	34	36	35
P-A	13	37	39	38
P-A	14	40	42	41
P-A	15	43	45	44
P-A	MX-1 Output	46	48	47
		49,50 Not Used		