



5043 Farlin Ave.
St. Louis, MO 63115

www.associatedequip.com



Product Bulletin

MODEL 3100A



Portable Smart Charger 6/12 Volt Full-Rate Charger With 100A Engine Start

Specifications:

Model Number	3100A
Type	6/12 V
DC Output	12V 15A Automatic 12V 2A Automatic 6V 8A Automatic 6V 2A Automatic
Engine Start	100 Amps
AC Cord	6' 18/3 – 120 VAC 60 Hz
Warranty	One Year Limited
DC Leads	6' 10/2 AWG
Weight	18 LBS
Shipping Dimensions	12" x 12" x 7.5"

Features:

- Automatic 6 & 12 Volt settings turn off at full charge and turn back on if battery needs more power
 - LED Digital Display indicates charging voltage, amperage, charge time and countdown for start function
 - Continuous rating 12V 15/2 Amps
 - 100A Engine Start 12V
 - Automatic bad battery detection
 - Automatic 6V position for lower voltage requirements
 - Designed for Standard, AGM, GEL batteries
 - Four-Color Retail Packaging
- Imported