

Portable Petrol Generator HYUNDAI HY2000Si

GENERAL FEATURES

• MODEL	HY2000Si	• KVA	Max kVA 2.0 @0.8pf
• TYPE	Portable	• FRAME	



DESCRIPTION

The Hyundai HY2000Si Petrol Inverter Generator is a simple to use source of portable power. With a massive 2000w / 2kW output and a low noise level of only 58dB you're assured of a clean, quiet, reliable source of power whether you're in a caravan, camping or a motor home. The HY2000Si comes with 2 standard 3 Pin sockets that will take any Australian 3 pin plug and also a 12V output for charging car or leisure batteries.

With the user in mind the lightweight, compact design incorporates a large carry handle and the tough exterior will protect against knocks and bangs, no matter what adventure you are on. The small footprint of this suitcase generator also makes it easy to store and simple to transport.

Like all Hyundai generators, the HY2000Si produces a pure sinewave output, so not only will it power your fridge or lighting but can handle much more sensitive equipment, such as TVs, laptop computers, tablets and smartphones.

CONTROL PANEL

LCD Display on Control Panel



Portable Petrol Generator HYUNDAI HY2000Si



TECHNICAL

• POWER OUTPUT KW/KVA	2000 watt Continuous / 2200 Watt Maximum / Max Kva 2.5 @0.8pf
• ENGINE DISPLACEMENT	80cc
• ENGINE MAKE	Hyundai
• ENGINE TYPE	IC80 - OHV, Single Cylinder
• FUEL TANK CAPACITY	3.8 Litres
• FUEL TYPE	4 - Stroke

FEATURES

- LCD Display Control Panel

COMES WITH

- 12v Charging Cables
- Oil Filling Bottle
- Spanner
- Screwdriver
- Instruction Manual

DIMENSIONS

- Length: 280 mm
- Width: 455 mm
- Height: 510 mm
- Weight: 21 kg

GENERAL RATINGS

VOLTAGE	POWER		NOISE LEVEL	RUN TIME	START Electric
	Max Output @ 0.8pf		dBA @7m see *1		
	kw	kva	dBA		
240	1.6k/w	2.0kVA	58	@75% Load	Recoil
				4 Hours	Recoil

*1 At 1/4 Load at 7m from control panel side