# Detachable Probe Sound Meter

840012 Instruction Manual




# CONTENTS

1	Introduction	. 3
2	Operating Instructions	
	2-A Measuring Procedures	. 4
	2-B Hold	. 4
	2-C Rec. Max/Min4	-5
	2-D Max. Hold	. 5
	2-E Signal Output	. 5
	2-F Calibration	. 5
	2-G Precautions	. 5
	2-H Auto Shut Off	. 6
	2-I Battery Replacement	. 6
3	Specifications	. 7
4	Warranty	. 8

#### 1. INTRODUCTION

Features a detachable probe for easy replacement and AC outputs. Also has A and C decibel frequency weighting scales, fast or slow time weighting, and two hold functions. Meets ANSI S1.4:2014 and IEC 61672:2013 for Type/Class 2 sound meters. Covers 30 to 130 dB in both Manual and Auto ranging scales with 0.1 dB resolution and an accuracy of ±1.0 dB. Calibrate in compliance with OSHA using Acoustical Calibrator 850016 or equivalent. Has a fold-out easel back and a tripod screw.

## 2. OPERATING INSTRUCTIONS



- 1. Microphone
- 2. Probe Holder
- 3. Probe Handle
- 4. BNC Plug
- 5. BNC Socket
- 6. LCD Display

- 7. Power Button
- 8. Hold Button
- 9. Rec./Max/Min
- 10. Max. Hold Button
- 11. A/C Button
- 12. Fast/Slow Button
- 13. Range Button
- 14. AC Output
- 15. Cal. Adjustment
- 16. Easel
- 17. Battery

#### 2-A. MEASURING PROCEDURES

- Connect the BNC PLUG to the BNC SOCKET.
- Slide the PROBE HANDLE into the PROBE HOLDER if desired.
- Press the POWER button to turn the unit on.
- The default mode is: Auto range, "A" frequency weighting and Fast time weighting.
- To change the frequency weighting, press the A/C button.
- The "A" frequency weighting simulates human ear response. For an environmental sound measurement, select the "A" weighting.
- The "C" weighting approximates a flat response. Often, "C" is used to check the noise of machinery where the target sound level is already known.
- Point the MICROPHONE at the sound source.
- Use the auto range setting (default) or find the appropriate range using the **RANGE** button.
- The manual selections are: 30 to 80dB, 50 to 100db, or 80 to 130db.
- If "----" is displayed, switch to another range. The sound level is displayed in decibels (dB).
- For general applications, press the **FAST/SLOW** button to select "Fast", simulating the human ear's response time.
- The "Slow" setting is generally used to obtain an average of vibrating sound levels.
- Press the POWER button to turn the unit off.

#### 2-B. HOLD

- During the measuring procedure, press the HOLD button to freeze the display.
- "HOLD" and the last measurement are displayed.
- Press the HOLD button again to exit this function.

## 2-C RECORD MAXIMUM / MINIMUM MEASURMENTS

- Press the REC MAX/MIN button once to enter the recording mode. "REC" and the recorded values are displayed and continuously updated.
- Press the REC MAX/MIN button as needed to view the recorded Max and Min values. "REC Max" and the maximum recorded value, or "REC Min" and the minimum recorded value are displayed.

#### NOTE:

The Max/Min values are frozen and not updated until the meter returns to recording mode.

- To return to recording mode, press the **HOLD** button. "REC" is displayed without "Max" or "Min".
- To erase the recorded Max/Min values and exit the recording mode, press the **REC MAX/MIN** button for at least 2 seconds.

## 2-D. MAX HOLD: (Holds the max measurement on the display.)

Press the **MAX HOLD** button, "P.H" appears on the LCD. Press the **MAX HOLD** button again to exit this function.

#### NOTE:

Select auto range when using this function in slow varying noise environments. Select the appropriate manual range when using this function in pulsing noise environments.

#### 2-E. AC OUTPUT

The 3.5 mm diameter **AC OUTPUT** may be used to connect the unit to an external output device, such as an analyzer, recorder, or controller.

#### 2-F. CALIBRATION

- The meter's CAL adjustment is located on the side of the unit.
- Use Sper Scientific's 2 Pt. Acoustical Calibrator 850016 (or equivalent) to calibrate the unit in compliance with OSHA.
- Press the **POWER** button to turn the unit on.
- Turn the acoustical calibrator on and place it onto the meter's MICROPHONE
- To calibrate the meter to 94 dB, select the 50 to 100 dB range, FAST response, and "A" weighting.
- Use the calibration screw driver to slowly turn the CAL adjustment until the display reads 94.0.
- To calibrate the meter to 114 dB, select the 80 to 130 dB range, FAST response, and "A" weighting and turn the **CAL** adjustment until the display reads 114 dB.

#### 2-G. PRECAUTIONS

- Do not store or operate the unit in high temperatures or in high humidity for long periods.
- Keep the microphone dry.
- Do not force the CAL adjustment, doing so may damage the mechanism and void the warranty.

#### 2-H. AUTOMATIC SHUT OFF

After approximately 10 minutes without activity (with no buttons pushed), the meter will automatically shut off. To disable this feature, press the **REC** button.

## 2-I. BATTERY REPLACEMENT

When the low battery icon is displayed, open the **BATTERY** compartment to install a fresh 9V alkaline or heavy duty type battery. In-spec measurements may be made for several hours after the icon appears.



# 3. SPECIFICATIONS

Display	2" x 1.25" LCD (52x32mm),
	5 digits with indicator.
Functions	dB ( A & C Frequency Weighting), Response
	(Fast, Slow), Hold, Memory (Min/Max), Max.
	Hold, AC Output
Measurement Range	30 to130 dB
Resolution	0.1 dB
Range Selector	30 to 80dB, 50 to 100dB, 80 to 130dB,
	50dB on each step, over/under range indicator.
	Auto Range: 30 to 130dB
Accuracy	±1.0 dB
Frequency	31.5 Hz to 8,000 Hz
Microphone	Electret condenser microphone,
	Dia5" (12.7mm)
Response	Fast (F): t = 200 ms
(Fast/Slow)	Slow (S): t = 500 ms
Calibration VR	Built-in external calibration VR for easy
	calibration using a standard 94 dB calibrator.
Output Signal	AC output: AC 0.5 Vrms corresponding
	to each range step.
Output impedance:	Slow (S): t = 500 ms
600 ohm	
Output Terminals	AC, 3.5mm diameter jack
Operating Temp.	32 to 122°F (0 to 50°C)
Operating Humidity	Less than 80% RH

# **SPECIFICATIONS** cont.

Power Supply	One 9V battery, heavy duty or alkaline type
Power	Approximately DC 6 mA
Consumption	
Weight	Weight: 8 oz (225 g) with battery
Dimension	Meter 10.6 x 2.7" x 1.1" (268 x 68 x 29mm).
	Probe 6.7" x 1" x .7" (170.5 x 24.5 x 19mm)
	Probe cord length: 78.7" (200cm)
Included Accessories	Windscreen, calibration tool, instructions, 9V
	battery, hard-shell foam-lined carrying case
Optional Services	840012C NIST Traceable Cert. of Calibration
& Accessories from	850016 2 Pt. Acoustical Calibrator
Sper Scientific	840091 Sound Meter Windscreen
	840090 Water Resistant Instrument Pouch
	840093 Field Tripod

#### 4. WARRANTY

Sper Scientific warrants this product against defects in materials and workmanship for a period of **five (5) years** from the date of purchase, and agrees to repair or replace any defective unit without charge. If your model has since been discontinued, an equivalent Sper Scientific product will be substituted if available. This warranty does not cover probes, batteries, battery leakage, or damage resulting from accident, tampering, misuse, or abuse of the product. Opening the meter to expose its electronics will void the warranty.

To obtain warranty service, ship the unit postage prepaid to: **SPER SCIENTIFIC LTD.** 

8281 E. Evans Rd., Suite #103 Scottsdale, AZ 85260 (480) 948-4448

The defective unit must be accompanied by a description of the problem and your return address. Register your product online at www.sperwarranty.com within 10 days of purchase.