


PSpice Model Varistor Panasonic ERZVA9V391



Model Information

Model A macro model

Call Name MDC ERZVA9V391 PS

Pin Assign 1:1 2:2

File List Model Library MDC_ERZVA9V391_PS01.lib

Model Report MDC_ERZVA9V391_PS.pdf (this file)

Verified Simulator Version

Note

PSpice version 17.2

References

The information which was used for modeling is as follow:

[Data Sheet]

Date/Version 2021/12/23Product name ERZVA9V391

● Company name Panasonic Corporation

Characteristics VflfTemp,VaristorVoltage,CapacitanceVr,ClampingCurrentW

aveform, Surge Current Waveform

Simulation Range

This table shows the range of evaluated simulation range that was not occurs any convergence problems in this area.

Item	Range			Unit
	Min.		Max.	
VaristorVoltage(typ)	390(at 1mA)	to	390(at 1mA)	V
ClampingVoltage(max)	650(at 25A)	to	650(at 25A)	V
Temperature	-40	to	125	deg C



O: Implemented

×: Not Implemented

—: Not applicable


Model Functions Table

Model Functions Table	RANK=1	. Not applicable
Functions	RANK	Implemented
IF-VF(Temp)	1	0
IR-VR(Temp)	1	0
Capacitance	1	0




Simulation results are following. Explanatory notes — : simulated

Vflf[Temp] (same Vrlr[Temp])




Varistor Voltage




CapacitanceVr

Freq = 1000Hz




Clamping Current Waveform





Simulation results are following. Explanatory notes — : simulated

Surge Current Waveform





DISCLAIMER

- 1. This SPICE (Simulation Program with Integrated Circuit Emphasis) model and its content (the "Contents") are copyright of MoDeCH Inc. All rights reserved. Any redistribution or reproduction of any or all part of the Contents in any form is prohibited without express written permission made by MoDeCH Inc.
- MoDeCH Inc. as licensor (the "Licensor") hereby grants to you, as licensee (the "Licensee"), a nonexclusive, non-transferable license to use the Contents as long as you abide by the terms and conditions of this DISCLAIMER.
- 3. The Licensee is not authorized to sell, loan, rent and redistribute or license the Contents in whole or in part, or in modified form, to anyone.
- 4. The Licensor shall in no way be liable to the Licensee or any third party for any loss or damage (including ,but not limited to, lost profits, or other incidental, consequential, or punitive damages), however caused (including through negligence) which may be directly or indirectly suffered from, arising out of, or in connection with, any use of the Contents.
- 5. Notwithstanding anything contained in this DISCLAIMER, in no event shall Licensor be liable for any claims, damages or loss which may arise from the modification, combination, operation or use of the Contents with the Licensee's computer programs.
- 6. The Licensor does not warrant that the Contents will function in any environment.
- 7. The Contents may be changed or updated without notice. MoDeCH Inc. may also make improvements and/or changes in the products, pricing and/or the programs related to the Contents at any time without notice.



MoDeCH Inc.

Head Office

Location: 5-15 Yokoyama-cho, Hachioji-Shi, Tokyo 192-0081, Japan

Tel:+81-42-656-3360

E-Mail:model-on-support@modech.co.jp

URL:http://www.modech.com/en/