N-Female to QMA-Female Adapter

by WAVEFORM

SKU: ADT-NF-QMAF



Main Features:

- N-Female to QMA-Female Adapter
- 0-6000 MHz
- **•** 50 Ω

Specifications:

Electrical:	
Input Impedance	50 Ω
Frequency Range	0 - 6000 MHz
Insertion Loss (Typical)	0.5 dB @ 6000 MHz

Clastyical.

Mechanical:	
Body Plating	Nickel
Connector Length	26.9 mm
Connector A Type	N-Female
Connector A Diameter	15.7 mm
Connector B Type	QMA-Female
Connector B Diameter	5.6 mm
Net Weight	20 g

Environmental:	
No	
Yes	

