



Model	Description	Power	USB Charger	Cutout Size
FM2/USB	2 Power 2 USB Flush Mount Power (Type A & C Smart Chargers)	2 x UK Sockets Fused at 5A	A & C USB (18W Max)	(L) 246 x (W) 63mm
FM4/USB	4 Power 2 USB Flush Mount Power (Type A & C Smart Chargers)	4 x UK Sockets Fused at 5A	A & C USB (18W Max)	(L) 376 x (W) 63mm
FM4/2USB	4 Power 4 USB Flush Mount Power (Type A & C Smart Chargers)	4 x UK Sockets Fused at 5A	A & C USB (18W Max)	(L) 418 x (W) 63mm
FM6/2USB	6 Power 4 USB Flush Mount Power (Type A & C Smart Chargers)	6 x UK Sockets Fused at 3.15A	A & C USB (18W Max)	(L) 548 x (W) 63mm
PC#	Power Lead - 13A UK Plug to 3 Pin Connector	Available in lengths from 1m to 10m (price dependent on length)		

### Product Description

- Finished in Black and Grey
- Individually fused to BS6396: 2008.
- UK sockets individually fused at 5A (20mm 5A Glass Fuse)
- USB Type A & C Smart chargers (QC3.0, PD 18W Max)
  - USB-A QC 3.0, 2V/5A, 5V/3A & 9V/2A
  - USB-C PD, 2V/5A, 5V/3A & 9V/2A.
  - Combined at 5V gives a constant 3.4A each
- FM6/4USB individually fused at 3.15A (20mm 3.15A Glass Fuse)
- 3 Pin input and output connectors
- Ratchet clamp system, fits desktops from 25-90mm
- Power and usb models can be daisy chained together
- Power cords fitted with 13A UK Plugs, available in various lengths are sold separately:
  - Cable Specifications:** 3 Core 1.5mm<sup>2</sup> 16amp rating

Contact: sales@floorbox.co.uk | Visit: www.floorbox.co.uk

Customer notice: Due to our policy of continuous improvement, Tass Cable Management Ltd reserve the right to change product specifications without notice. Tass Cable Management Ltd © | Floorbox.co.uk © | 2023 | All rights Reserved.