

VX 520 TIPS

CHANGING VX 520 PARAMETERS

COLUMN PRINT WIDTH

There are two options available – 32 column and 42 column. The column number represents how many characters print in a line, 32 characters would be slightly larger.

- 1. From the main menu, press the green ENTER key to get to configuration menu
- 2. Select Other Setup
- 3. Choose Printer
- 4. Keep pressing NEXT until you see Column Mode

PRINT HUE

While paper plays a huge factor in the quality of print, users can adjust the print hue by setting a parameter. The *DARK parameter controls the contrast of the output to the printer. This parameter should be added to GID 1 config.sys either in the VeriCentre download template or through Edit Parameters in system mode directly on the terminal. The optimal value for *DARK is 5.

If setting the parameter in your VeriCentre download template, it should be included with the VMAC parameters in GID 1.

If setting the parameter in config.sys within the o/s of the terminal, follow the steps below:

- 1. In system mode, choose (1) Edit Parameters
- 2. Press Enter to select Group 1
- 3. Enter the Group 1 password
- 4. Press Enter at "File: CONFIG.SYS"
- 5. Press (1) to add a New Parameter
- 6. Enter the name of the parameters (*DARK) and press Enter
- 7. Enter the value which should be 5 for optimal output and press Enter
- 8. Press the red Cancel button to return to the Verix Terminal MGR menu
- 9. Select (3) for Restart

© 2015 Verifone, Inc. All rights reserved. Verifone, the Verifone logo and VX are either trademarks or registered trademarks of Verifone in the United States and/or other countries. All other trademarks or brand names are the properties of their respective holders. All features and specifications are subject to change without notice. Product display image for representation purposes only. Actual product display may vary. Reproduction or posting of this document without prior Verifone approval is prohibited. 8/15 FS

