

MIXER AMPLIFIER | MA-60PR AMPLIFIER

60W MIXER AMPLIFIER WITH USB,
TUNER & BLUETOOTH

ALHAAN



The MA-60PR is a compact and versatile 60W Mixer Amplifier with USB, Tuner & Bluetooth, which offers the finest sound quality at the most competitive price. It is easy to use with modern state of the art features like priority function, volume control, chime function, etc. It is quite popular for commercial background music and paging purposes, ideal for mid-sized locations such as schools and offices. More reliable than other models, this Mixer Amplifier does not compromise on features such as priority and flexibility.

FEATURES

- ▶ Three line and two microphone inputs with Euro block and RAC jack.
- ▶ Acceptable wide range input level.
- ▶ 60Watts rated power output.
- ▶ Advanced protection system includes current limiting, over current and thermal protections.
- ▶ Desktop and 19-inches rack mountable type.
- ▶ Two bands tone controls.
- ▶ Low distortion and low noise level.
- ▶ Compact size and light weight.
- ▶ Ideal commercial and industrial use.



TECHNICAL SPECIFICATIONS

MODEL	MA-60PR	
Rated Output Power	60W	
Input sensitivity / Impedance	Mic	-50dB/600ohm
	Line	6dB/10kohm
Power Supply Voltage	100-240V 50/60Hz	
Power Consumption	70W	
Speaker Output	100V(166Ω),70V(82Ω),4Ω(15V)	
Frequency Response	80Hz-17KHz (+1dB /-3dB)	
S/N Ratio	>80dB (with A-Weight)	
T.H.D	<1 at rated power, 1kHz)	
Auxiliary input	0dBu/10KΩ, unbalanced input	
Tone Controls	Bass:100Hz(±10dB), Treble:10KHz(±10dB)	
Mute Function	MIC over other inputs	
Working Temperature	-10° C~+ 40° C	
Product Dimension (WxHxD)	280x60x200 mm	
Net Weightt	5.0kg	

