

MIXER AMPLIFIER | SMA-250PR

250W PRIORITY MIXER AMPLIFIER

ALHAAN



The SMA-250PR 250W Mixer Amplifier is a highly cost-efficient model for public address systems which is used in large meeting rooms, shops, factories, mosques etc where broadcasting paging and background music needs to be provided. More reliable than other models, this Mixer Amplifier does not compromise on features such as priority and flexibility. . It is easy to use with modern state of the art features like priority function, volume control, chime function, etc. It supports 5-zones with individual volume controls of each zone.

FEATURES:

- ▶ 2 microphone inputs, 3 line inputs and 1 line output.
- ▶ 100V, 70V, 4-16Ω output with LED screen.
- ▶ Control the volume of each of the 5 separate zones flexibly.
- ▶ USB interface. SD, Bluetooth and audio can be switched randomly.
- ▶ Easy to insert priority broadcast with monitoring and muting function.



TECHNICAL SPECIFICATIONS

MODEL	SMA-250PR
Rated Power	250W
Rated Output	70V 4-16Ω 100V
FR	40Hz-16KHz
Input	-52dB -10dB
SNR	≥80dB
Output Level	-10dB
Monitor Output	+4dB
Power	AC220V±10% 50Hz

