

DIMMER TESTING WITH: LEDR8012W

DATE: 18.3.20

DIMMER BRAND	DIMMER MODEL	PASS/FAIL	MAX LUX WITH NO DIMMER IN CIRCUIT	MAX LUX LEVEL WITH DIMMER IN CIRCUIT 100%	MIN LUX WITH DIMMER	% WHEN DIMMER ON MINIMUM SETTING	COMMENTS
HPM LEGRAND	EM400A2P	FAIL					UNSTABLE
	EM400A3P	PASS	110	108	0	0%	SMOOTH
	EM400TR	PASS	110	110	0.1	0%	SMOOTH
	EM700TR	PASS	110	110	0.2	0%	SMOOTH
	EM250TR	PASS	110	110	0.1	0%	SMOOTH
PDL	PDL354PBDMBW	PASS	110	39.5	0	0%	SMOOTH
	PDL354PBDMUN	FAIL	110	110	7.7	7%	FLICKERS
	PDL354RDMLED	PASS	110	110	0	0%	SMOOTH
	PDL624M	PASS	110	110	0.1	0%	SMOOTH
	PDL654M	PASS	110	110	5.3	5%	SMOOTH
KIWI	K005U	PASS	110	110	0.1	0%	SMOOTH
GERRARD	MEDM	PASS	110	110	0	0%	SMOOTH