


Smart Wi-Fi dimmer switch

Single pole



Manual and remote dimming control



Single pole only
Not compatible with 3-way (multi-location control) circuits



Voice control
Requires an Amazon Alexa or Google Assistant-enabled device



No hub required



Easy to share access



Your home in **one app**

The easiest way to make your existing lights smart

Nexxt Solutions introduces its new **Smart Home Automation Series**. Designed to suit your mobile lifestyle while building a safe environment inside and out of your home, the brand seamlessly unifies into one user-friendly application a comprehensive line of fully integrated devices. From smart plugs, cameras, bulbs and photo frames to security kits, you can now take control and run your home devices, on your own schedule even when you are not there.

Customizing your lights and favorite scenes has never been easier! Designed to replace/upgrade conventional single-pole light controls, our **Smart Wi-Fi dimmer switch** can be quickly installed and integrated into your existing wireless network, *no hub required*. Boasting a modern design along with its fire-retardant construction, this switch emerges as a great addition to any room in the home. Since it's powered by the Nexxt Solutions Home app, users can remotely monitor their lights, tailor the brightness level and set on/off times using a smartphone, at any time and from anywhere. Its voice activation feature makes it compatible with Google Assistant and Amazon Alexa for hands-free management of all linked devices. You can have peace of mind by checking the real-time status of any appliance at any time, save energy by running your house on your schedule, while providing a higher sense of security by making it appear that you are home even though you are half way around the world.

Highlights

- **Smart dimmer switch**
- Designed for energy-efficient LED and conventional incandescent bulbs
- Manual and remote on/off, dimming controls through the app
- Full-dimming range with memory function
- Discreet slider for precise and smooth brightness level adjustment
- Convenient LED indicators display the brightness level
- Single pole, for lights controlled from one location
- Nexxt Solutions Home App
- iOS and Android™ platform compatible
- No hub required
- Easy pairing
- **Voice activated:** utter simple commands using your favorite voice assistant
- **Create schedules:** turn lights on or off, or set illumination levels at specific times, or based on sunrise - sunset cycles
- Multiple programmable timers
- Share access



Smart Wi-Fi dimmer switch

Single pole



Technical specifications

MPN	NHE-D100
Input	
Nominal voltage	100-240V
Frequency	50/60Hz
Amperage	15A
Load capacity	150W (LED bulb), 500W (INC-tungsten bulb)
Wireless frequency	IEEE 802.11N, 2.4GHz (not compatible with 5GHz Wi-Fi networks)
Output	
Nominal voltage	100-240V
Frequency	50/60Hz
Physical features	
Dimensions	4.9x3.14x1.65in
Housing	ABS and PC fire retardant plastic
Color	White
Weight	6.3oz
Environment	
Operating temperature	-13 -167 °F
Storage temperature	-13 -167 °F
Relative humidity	<75%
Additional Information	
System requirements	<ul style="list-style-type: none">• Mobile device running iOS8 or higher, Android™ 5.0 or higher• Nexxt Home app• Existing Wi-Fi network
Certificate	FCC, ETL
Warranty	Two years

- Not designed to be used with metal face plates, as it may interfere with the Wi-Fi signal
- Does not support CFL bulbs
- All LED and incandescent bulbs must be dimmable