



Televes reserves the right to modify the product

V Zenit MIX antenna

High-VHF/UHF

Two antennas in one

The V Zenit MIX antenna combines two antennas in one for a mixed reception. The UHF part consists in a V-type structure, formed by two vertically stacked Yagi in phase, which provides an exceptional relation between gain and compactness. Additionally, a dipole and specific reflectors are added for High-VHF reception.

Ref.149381

Art.Nr

EAN13

8424450184455

Highlights

- Quick and secure reflector assembly system
- Robust mechanics with outstanding performance in vibrating situations
- Compact: excellent ratio between gain and length
- Flatness of the frequency response in the UHF band

Discover

- Built with aluminium (corrosion resistant) for a long service life, and in ABS plastic for high weather resistance
- The mast-mounting system utilizes Zamak to provide sturdiness and stability in adverse weather conditions
- Designed and manufactured in Europe, our products undergo the most stringent quality controls
- The connection box includes a balun for impedance matching

Technical specifications

Operating band	MHz	174...216 (C 7-13)	470...698 (C 14-51)
Gain	dBi	8.5	13
Front-to-Back ratio	dB	> 12	> 23
Wind load	N	96 (@ 80 miles/h) 132 (@ 93 miles/h)	