

# **JBL / VMA 260**

8 Inputs, 2X60 Watt, Bluetooth, USB, 2RU





The JBL VMA Series is a cost-effective line of Mixer/Amplifiers with low impedance functionality (4?, 8?) and high impedance 70V and 100V output. They are designed with convenient and flexible features to be used by commercial integrators worldwide, ideal for emerging markets.

- Enables easy connection with USB-compatible devices
- Listen to deep lows and extreme highs maintaining 20 kHz maximum frequency
- Helps maintain the signal's strength
- · Paging Chime, and Priority muting
- Works with JBL CSR-V wall controllers
- Balanced mic/line inputs; RCA (.775V) inputs
- · Rack mounting hardware included

# **JBL / VMA 260**

8 Inputs, 2X60 Watt, Bluetooth, USB, 2RU

IFRAI		

Manufacturer Part Number VMA 260

Manufacturer Website Address http://www.harman.com

**Brand Name JBL** 

**Product Line** Commercial

**Product Series** VMA

Product Model VMA260

Product Name Commercial VMA260 Amplifier

Product Type Amplifier

## **TECHNICAL INFORMATION**

Minimum Frequency Response 20 Hz

Maximum Frequency Response 20 kHz

**Total Harmonic Distortion (THD)** 0.5%

## **AUDIO**

Audio Channels 2

RMS Output Power 120 W

#### **NETWORK & COMMUNICATION**

Ethernet Yes

#### **INTERFACES/PORTS**

USB Yes

Number of Analog Audio Inputs 8

# **POWER DESCRIPTION**

Operating Power Consumption 225 W

### **MISCELLANEOUS**

Package Contents | Commercial VMA260 Amplifier Rack mounting hardware

**Environmentally Friendly Yes** 

**Environmental Certification WEEE** 

Country of Origin China

## **ITEM DETAILS**

Category Pro Audio

**UPS Shippable** Y

Shipping Weight 12