

13-1F-W





13-4F-B

13-4F-W

13-5F-B

13-5F-W

# **FLUSH 1 GANG SWITCH GRID**

13-1F-B/W

Recessed, trimless, and completely flush switch plates to suit all applications integrate with surrounds.

#### SPECIFICATIONS

DIMENSIONS MATERIAL REGION APPLICATION GANG NO. WEIGHT CAPSULE CUTOUT IP MINIMUM MOUNTING DEPTH

STANDARDS COMPLIANCE NUMBER PRODUCT CERTIFICATION PATENT

## FINISHES



BLACK [W] [B]

H46 X W132 X D11 mm POLYCARBONATE AU/NZ INTERIOR 1 GANG\* 30.25 g SEE MOUNTING ACCESSORY IP20 SEE MOUNTING ACCESSORY

SGS-170519-EA RCM 2018203470

AS/NZS 3112, 3100, 60950

COMPATIBLE ACCESSORIES INDEX

 PRODUCT	SKU	
FLUSH FIXED MOUNTING	13-FMA	
FLUSH ADJUSTABLE MOUNTING	13-AMA-B/W	
FLUSH FIRE RATED ENCLOSURE	13-FRE*	

\*MECHANISMS NOT INCLUDED.

NB. SWITCHGRID FINISH TO MATCH 13-AMA COLOUR. \*13-FRE MUST BE INSTALLED IN CONJUNCTION WITH 13-FMA/AMA.



#### ORDER GUIDE

SERIES			TYPE		COLOUR
E.G.	13		1 GANG FLUSH		BLACK
CODE	13	-	1F	-	В


### PACKAGING SPECIFICATIONS


INDIVIDUAL PACK SIZE GROUP PACK PCS GROUP PACK SIZE BULK PACK PCS BULK PACK SIZE D123 X W200 X H65 mm 10 D137 X W150 X H53 mm 100 D280 X W315 X H150 mm

#### **CLEANING & MAINTENANCE**

To clean, simply wipe with a soft damp cloth or detergent-impregnated wipes. Under no circumstance should you spray cleaning solution directly onto the product or use abrasive or solvent type cleaners. If you notice deterioration or damage to this product over time, contact a licensed electrician to repair and/or replace the damaged product immediately.







46

