Comsec Protection Systems



Overdoor Light c/w Sounder

Part No. NC806CS



Overview

Provides audible and visual indication of 800 Series Alarm calls outside bedrooms, WCs and any other area fitted with an 800 Series calling device.

Indicates Standard calls via a constant tone/constant red light and Emergency calls via a pulsing tone/pulsing red light.

Dual red LEDs and triangular diffuser make it highly visible from a distance.

Mounts on a standard UK 25mm single gang flush or surface back box.

Can also be used as an 'area indicator' at corridor junctions, staff workstations, etc.

Finished in tough, durable ABS plastic.

Also available as part of the NC951 Accessible Toilet Alarm kit.

Stainless steel version also available

Technical Specifications

Quiescent current	OmA (none).
Alarm current	Determined by the type of control equipment and number \prime type of field devices connected to the system.
Indicators	Dual ultra-bright red Alarm LEDs (lit constantly for standard calls, intermittently for emergency calls).
Controls	None (the device is controlled by the master calling device it is connected to).
Connections	1 (Signal); -Ve (Negative); +Ve (Positive).
Onboard Sounder	Yes. Sounds constantly for standard calls, intermittently for emergency calls.
Onboard Infrared Receiver	No.
Product dimensions (mm)	87W x $87H$ x $68D$ mm. Mounts on a UK 25mm single gang back box.
Construction & finish	Plastic.
IP Rating	IP41
Weight	52g.

ISCE The relate of Sound and Communications Engineers



T 01942 322744 E sales@c-tec.co.uk

F 01942 829867 W www.c-tec.com

C-TEC, Challenge Way, Martland Park, Wigan, WN5 0LD United Kingdom

Comsec Protection Systems



Operating conditions/temperature

-5°C to +40°C. Max. relative humidity 95% non-condensing.



 T
 01942 322744
 E
 sales@c-tec.co.uk

 F
 01942 829867
 W
 www.c-tec.com





C-TEC, Challenge Way, Martland Park, Wigan, WN5 0LD United Kingdom

Comsec Protection Systems





T 01942 322744 **F** 01942 829867

E sales@c-tec.co.uk W www.c-tec.com



 $\overbrace{\underbrace{\operatorname{Ker}}}^{\operatorname{Ker}} \left[\underbrace{\operatorname{Ker}}_{\operatorname{Ker}} \right] \left[\operatorname{Ker}}_{\operatorname{Ker}} \right] \left[\operatorname{Ker}}_{\operatorname{Ker} \right] \left[\operatorname{Ker}_{\operatorname{Ker}} \right] \left[\operatorname{Ker}_{\operatorname{Ker}} \right] \left[\operatorname{Ker}} \right] \left[\operatorname{Ker}}_{\operatorname{Ker}} \right] \left[\operatorname{Ker}}_{\operatorname{Ker}} \right] \left[\operatorname{Ker}}_{\operatorname{Ker}} \right] \left[\operatorname{Ker}}_{\operatorname{Ker} \right] \left[\operatorname{Ker}_{\operatorname{Ker}} \right] \left[\operatorname{Ker}} \left[\operatorname{Ker}}_{\operatorname{Ker}} \right] \left[\operatorname{Ker}}_{\operatorname{Ker}} \right] \left[\operatorname{Ker}}_{\operatorname{Ker} \right] \left[\operatorname{Ker}_{\operatorname{Ker}} \right] \left[\operatorname{Ker}} \left[\operatorname{Ker}} \right] \left[\operatorname{Ker} \right] \left[\operatorname{Ker}} \left[\operatorname{K$

