



Art.-No.: YMOCA-CASADIMM
Casa Trailing Edge Dimmer Bluetooth control module,
max. 150W LED / 200W ohmic, IP20

NEWS!



The CASA trailing edge dimmer is a trailing edge dimmer. Its use enables stepless dimming of trailing-edge lamps. Output power 150W LED / 200W ohmic (e.g. light bulbs). It is controlled wirelessly with the CASAMBI® app.

TECHNICAL DATA

Electrical data	
Input Voltage AC	AC 220-240V / 50-60Hz
Consumption standby	0.5 W
Output max.	150 W
Connection cross section	2.5 mm ²
Load types	Capacitive load
Communication type	Wireless, Casambi
Dimming	TRIAC
Frequency band	2,403 - 2,479 GHz
max. transmission power	+4 dBm
CASAMBI Inside	Yes
Acceptance tests	
Certifications	CE
Protection class	II
Ingress protection (IP) rating	IP 20
Ambient temperature	-20 to +50 C°
Housing temperatur max., tc	60 C°



Physical data	
Housing material	Polycarbonate
Housing colour	white
Length (L)	143 mm
Width (B)	47 mm
Height (H)	29 mm
Packaging Length (L)	162 mm
Packaging Width (B)	51 mm
Packaging Height (H)	31 mm