

SuperBase V 6400

1. 6.4kWh Capacity with 3,800 AC Output, expand up to 64kWh Capacity with 7,600W AC Output
2. More Efficiency:
 - a. Multiple Charges Max 6,600W, Input 6.6KWh in 1-hour
 - b. The Industry's Fastest 3,000W Solar Input
 - c. Fast-charging EV at Level 2
3. Reliable and Flexible Power Solutions:
 - a. 120V/240V Dual Voltage Output in One Unit
 - b. Seamless UPS
 - c. EV-Grade Semi-solid State Batteries
 - d. Charge temperatures compatible from -20°C to 45°C



Specifications:

Name :	Model :
SuperBase V	ZDSBV6400
Capacity :	Size :
6,438Wh	73 x 34.6 x 44.2cm
Battery type	Color
Semi-solid State	Gray
AC Input :	DC Input :
15A Max, 120VAC 1800W or 240VAC 3600W ZenT2 Input: 100-240VAC, 3600W Max (EV T1 Adapter needed)	XT90 Input: 12-150V=25A, 3000W Max
Output :	
Total AC Output: 3800W rated 4x 5-20: 120VAC, 15A 1x 6-20: 240VAC, 16A 1x TT-30: 120VAC, 30A 1x Car Outlet : 12.6V=10A, 126W Max 2x DC5521: 12.6V=3A	1x Andersen: 12.6V=30A, 378W Max USB-C(1)/(2): 5V-20V, 100W Max each USB-C(3)/(4): 5V-12V, 20W Max each USB-A(1)(2): 5V2.4A total
Charge Temperature	Discharge Temperature
-20°C to 45°C / 0°C to 45°C	-20°C to 45°C
Weight:	LED light :
130lbs (59kg)	RGB; Lighting
Wi-Fi:	Bluetooth:
Yes	Yes
In The Box :	
AC cable, MC4 to XT90 cable, Car charging cable, Accessory pouch	

Name :	Model :
Satellite Battery	ZDSATB6400
Capacity :	Size :
6,438Wh	69 x 28.5 x 27.4cm
Battery type	Color
Semi-solid State	Gray
DC Input :	Output :
XT90 Input: 12-150V=10A, 600W Max	1x Car Outlet : 12.6V=10A 1x Andersen: 12.6V=30A, 378W Max XT90: 12-60V=10A, 600W Max (App enabled)
Weight:	LED light :
101lbs (46kg) / 98.7lbs (44.8kg)	RGB; Lighting
In The Box :	
Handle Cover, MC4 to XT90 cable	
More:	Smart APP compatible