



## Aurelia Bold S 22 LED Pendant

Patrick Jouin, 2021

Aurelia (scientific latin genus of the jelly fish) was designed for Leucos in 2021 by the esteemed Patrick Jouin (Ether, Reed and Mercure). Aurelia's translucent jelly fish shaped glass body floats through space trailing light via a direct light down its hand finished metal funnel while a hidden indirect LED ring on top of the funnel illuminates the hand-blown glass diffuser. Both direct and indirect lighting elements (user replaceable integrated LEDs) are independently dimmable creating the ability to create atmospheric mood lighting, functional down light or any combination of the two.

### Diffuser Finish Options:

Transparent  
 Smoke Grey

### Structure Finish Options:

Gloss Warm White  
 Matte Gunmetal  
 Vintage Brass

### SKU(s):

0011513	Smoke Grey/Gloss White, 2700K
0011511	Smoke Grey/Matte Gunmetal, 2700K
0011509	Smoke Grey/Vintage Brass, 2700K
0011507	Transparent/Gloss White, 2700K
0011505	Transparent/Matte Gunmetal, 2700K
0011503	Transparent/Vintage Brass, 2700K
0011501	Smoke Grey/Gloss White, 3000K
0011499	Smoke Grey/Matte Gunmetal, 3000K
0011497	Smoke Grey/Vintage Brass, 3000K
0011495	Transparent/Gloss White, 3000K
0011493	Transparent/Matte Gunmetal, 3000K
0011491	Transparent/Vintage Brass, 3000K

### Dimensions:

Width: 8.875 in  
 Depth: 8.875 in  
 Height: 9.5 in  
 Weight: 8.8 lbs  
 Cord Length: 118 in

### Shipping:

Weight: 12.3 lbs  
 Parcels: 1 Parcel  
 Volume: .13 ft<sup>3</sup>  
 Service: Small Parcel

### Materials:

Hand-blown Glass, Metal

### Certifications:

ETL

### Family Includes:

Aurelia S 45 Pendant  
 Aurelia Bold S 22 Pendant

### Lamping 1: 2700K Integrated LED

Wattage: 20.4 W  
 Total Lumens: 2433 lm  
 Direct Lumens: 1663 lm  
 Indirect Lumens: 770 lm  
 CCT: 2700 K  
 CRI: >90  
 Voltage: 120/240V  
 Dimming: Push Dim; 0/1-10V

### Lamping 2: 3000K Integrated LED

Wattage: 20.4 W  
 Total Lumens: 2499 lm  
 Direct Lumens: 1700 lm  
 Indirect Lumens: 793 lm  
 CCT: 3000 K  
 CRI: >90  
 Voltage: 120/240V  
 Dimming: Push Dim; 0/1-10V

### Special Notes:

Direct and indirect lighting can be controlled independantly.

LED modules are user replaceable.

Made in Italy



[Additional Info/Images](#)