

PRODUCT

Manufacturer	inactive
SKU	PM0497000
Model Number	PM0497000
Generator Grade	Semi-Professional
Generator Style	Portable Generator
Special Features	30 Amp Plug, Built In America, Fuel Gauge, Wheel Kit

ENGINE DETAILS

Engine/Motor Brand	Honda
Engine Model	GX389
Fuel Type	Gasoline
Starting System	Recoil/Pull
Horsepower	11.0 HP
Engine/Motor Type	OHV
Displacement	389cc
Engine RPM	3600 RPM
Fuel Capacity	8.00 Gallons

Run Time @ 50% Ld (Hrs)	12.4
Fuel Cons. @ 50% Ld	0.65 Gallons/Hour
Fuel Gauge	Included
Enclosure	Tubular Steel
Fuel Tank Material	Metal
Low Oil Shutdown/Alert	Yes
Engine Cyl. Sleeve Mtrl.	Cast Iron

ACCESSORIES

Portability/Wheel Kit	Included
Portability Handle(s)	Fold-Away
Cover	Add @ Checkout
Gas Can	Add @ Checkout

WARRANTY

Engine Warranty	3 Years
Consumer Generator Warranty	2 Years
Commercial Generator Warranty	1 Year

ORIGIN

Built In	United States
-----------------	---------------

OTHER INFORMATION

Weight (Lbs.)	186
Unit Dimensions	30.5"L x 20.8"W x 24.8"H
Ship Dimensions (Box)	31.3"L x 20.9"W x 24.3"H
Agency Compliance	EPA
EAN	8018539055745

OUTLETS

NEMA 5-20R Duplex (20 Amp 120, 2 Each)



NEMA L14-30R (30 Amp 120/240)



GENERATOR DETAILS

Surge Start Watts	8,750.0
Continuous Rated Watts	7,000.0
Phase	Single-Phase
Voltage	120, 240
Rated Amps @ Min Volt (Commonly 120v)	58.3
Rated Amps @ Max Volt	29.2
Frequency	60 Hz
Voltage Regulation	Auto Voltage Regulation
Circuit Breakers	Yes
Bonded Neutral (Y/N)	Bonded Neutral To Ground