

# Digital Multimeter

## HTC – MAS830L

**HTC**<sup>TM</sup>  
**INSTRUMENTS**

### Features:

- 3 ½ Digit LCD Display with backlighting
- Data Hold
- Transistor & Diode Test
- Overload Protection
- Low Battery Indication



### Technical Data :

Basic Functions	Range	Basic Accuracy
DC Voltage	200mV/2V/20V/200V/600V	±(0.8% + 2 Digits)
AC Voltage	200 / 600V	±(1.5% + 10 Digits)
DC Current	200μA/2mA/20mA/200mA/10A	±(1.0% + 10 Digits)
Resistance	200Ω/2kΩ/20kΩ/200kΩ/2MΩ	±(0.8% + 2 Digits)
Diode Check	3V / 0.8mA	
hFE (NPN or PNP)	0 ~ 1000	

- **Standard Accessories** : Manual, Test leads, 9 Volt Battery, Holster
- **Dimension** : 69(H) x 138(W) x 31(D)mm
- **Weight** : Approx 170 gm