## KERNMASTER...

Static-rappelling Kernmaster line is constructed with a traditional "mantle" sleeve consisting of 48 strands of polyester. The inside, or "kern," is a braided core of energy-absorbing nylon. The core is fully steam-stabilized to enhance the rope's flexibility and prevent hardening in service; the braid also bends more easily and


with less fatiguing of the core when cycled over sheaves or dropped over a parapet. Sleeve is either white or solution-cast fiber (color added prior to yarn production) which makes for lasting colors and enhanced wear resistance. **Standards:** 11mm, 12mm: CE0120 EN1891 Type A

Diameter		Average		Minimum		Working Load		Weight	
Inches (mm)	<b>Break Strength</b>		Break Strength		for Rigging		Lbs/	Kg/	
	Lbs	Kg	Lbs	Kg	Lbs	Kg	100ft	100m	
3/8" (9mm)	4,245	1,925	3,821	1,733	849	385	2.3	3.4	
7/16" (11mm)	7,100	3,220	6,390	2,905	1,420	644	5.5	8.2	
1/2" (12mm)	9,200	4,182	8,600	3,910	1,840	836	7.6	11.4	
5/8" (16mm)	12,500	5,682	11,250	5,682	2,500	1,136	11.4	17.0	

\* Knots and abrupt bends significantly reduce the strength of all ropes and lowers maximum working load.

\* For situations where a man is on the rope, cut these working loads in half. Working load is based on static or moderately dynamic lifting/pulling operations. Instantaneous changes in load up or down, in excess of 10% of the rope's rated working load constitutes hazardous shock load and would void normal working load recommendation. Consult Yale Cordage for guidelines for working loads and safe use of rope.

**Average Break Strength** 



Specific Gravity: 1.23

## **Energy Absorption**

The colored area under the curve represents the rope's energy-absorption capability.

- Green working 622 ft. lbs./lb.
- Red ultimate 9,775 ft. lbs./lb.

Dielectric Strength: The maximum allowable leakage for clean, dry Kernmaster is 500 Micro Amperes when tested at 90KV per ASTM 1701-05 "Routine Production Test". Absorbed and entrained moisture or impurities will increase ropes conductivity dramatically.

Available with factory splices.