

INDUCTIVE SENSOR CHIP IMMUNE DW-Ax-71x-M18-967


HOUSING	OPERATING DISTANCE	MOUNTING
M18	5 mm	Non-embeddable


 Immune to metal chips: steel, aluminum, copper, stainless steel, brass, titanium

- ✓ One-piece housing in stainless steel V2A
- ✓ IP68 and IP69K
- ✓ IO-Link v1.1









DW-AS-71x-M18-967

DETECTION DATA		INTERFACE			
5 mm	Indicator LED, yellow	Sensing state (0 \leq s \leq 0.8 S,			
\leq (0.81 x S _n) mm	Indicator LED, yellow, blinking	Sensing state (0.8 $S_r < s \le S_r$)			
≤ 0.35 mm	IO-Link	\checkmark			
3% S _r ≤ Hyst ≤ 15% S _r	MTTF (@40°C)	1028 y			
\leq 10% S _r					
18 x 18 x 1 mm ³ , FE360					
	≤ (0.81 x S _n) mm ≤ 0.35 mm 3% S _r ≤ Hyst ≤ 15% S _r ≤ 10% S _r				

Note: $0.9S_n \le S_r \le 1.1S_n$.

ELECTRICAL DATA

Supply voltage range (U_B)	1030 VDC	Mounting	Non-embeddable
Residual ripple	\leq 20% U _B	Housing material	V2A / 1.4305 / AISI 303
Output current	≤ 200 mA	Sensing face material	V2A / 1.4305 / AISI 303
Output voltage drop	\leq 2.0 VDC	Max tightening torque	50 Nm
Power consumption (no-load)	≤ 10 mA	Ambient operating temperature	-25+85°C1
Residual current	≤ 0.1 mA	Enclosure rating	IP68 / IP69K
Switching frequency	≤ 200 Hz	Weight (cable/connector)	see page 2
Short-circuit protection	\checkmark	Shock and vibration	IEC 60947-5-2 / 7.4
Voltage reversal protection	\checkmark		
Cable length max.	≤ 300 m		

¹Maximum temperature according to UL: 70°C.

Note: all data measured according to IEC 60947-5-2 standard with U_{_B}=20\ldots 30VDC, T_{_A}=23^{\circ}C\pm5^{\circ}C.

CORRECTION FA	CTORS FO	R TARGET OF							
Steel FE 360	1	Copper	1.5	Aluminum	1.7	Brass	1.7	Stainless Steel V2A 1/2 mm	0/0.2

INSTALLATION CONDITIONS b Α С B. d ſ A : metal free zone a: 10mm d:steel 23mm B : sensing face b: 80mm C : support c: 15mm

IO-LINK FUNCTIONALITIES

IO-Link version	1.1
SIO mode	Supported
Process data	7-bit input
Baudrate	COM2 (38.4 kBaud)
Minimum cycle time	10.4 ms
ISDU	Not supported



IODD files may be downloaded from

www.contrinex.com/product-range/inductive-sensors/.


Select the product name to display the product page with corresponding downloads.

Alternatively, just click/scan the QR code on the left.

PIN ASSIGNMENT

Note: additional installation information can be found in the glossary of the Contrinex General Catalog.

WIRING DIAGRAM





AVAILABLE TYPES

Part number	Part reference	Polarity	Connection	Output on pin 2	Output on pin 4 / bk	Weight
320-420-759	DW-AS-711-M18-967	NPN	M12 4-pin	-	Normally open (NO)	53 g
330-320-102	DW-AS-713-M18-967	PNP	M12 4-pin	-	Normally open (NO) / IO-Link	53 g

Note: part reference may include additional suffix to indicate a revision version or special version. Further information is available on request.

Operators of the products we supply are responsible for compliance with measures for the protection of persons. The use of our equipment in applications where the safety of persons might be at risk is only authorized if the operator observes and implements separate, appropriate and necessary measures for the protection of persons and machines. Terms of delivery and rights to change design reserved.

CONTRINEX AG Industrial Electronics

Route du Pâqui 5 - P.O. Box - CH 1720 Corminboeuf - Switzerland - Tel: +41 26 460 46 46 Fax: +41 26 460 46 40 - Internet: www.contrinex.com - E-mail: info@contrinex.com

DW-Ax-71x-M18-967_Rev 1_11.02.2020_DW-TGF