

SPECIFICATION SHEET

JOB NAME:

LOCATION:

QUOTE/REF#:



DESCRIPTION

12V DC LED Plug-In Constant Voltage Drivers are generally used when you need stable voltage to your LED lights. It has built-in overload, short circuit, and overheat protection. They are energy efficient and ideal for powering our 12V DC LED lighting. Available in 12 watts, 24 watts, or 36 watts options.

Need help with your LED lighting applications? Our lighting experts are here to help! Contact us today for assistance with lighting plan or installation instructions.

SPECIFICATIONS

Input:	100-240V AC
Output:	12V DC
Power:	12, 24, or 36 Watts Options
Dimmable:	No
Class II:	Yes
Power Method:	Plug N Play
Driver Size:	3.5 in. L x 1.5 in. W x 1 in. H 89 mm L x 38 mm W x 25 mm H (12 or 24 Watt)
Driver Size:	3.5 in. L x 1.75 in. W x 1.5 in. H 89 mm L x 44 mm W x 38 mm H (36 Watt)
Finish:	Black Polycarbonate
Environment:	Dry Location
IP Rating:	IP20
Rating:	UL Listed, CUL Listed, RoHS, CE
Manufacturer:	Elumalight
Warranty:	1 Year Limited

KEY FEATURES

- Easy installation - Plug N Play
- Maintenance-free Class 2 drivers
- Solid-state construction
- High vibration and shock resistance
- Overload, short circuit, and overheat protection
- No RF interference
- Comes with ~5 ft length output cable
- Output Male DC barrel plug is 2.5 mm
- UL Listed power supply
- Long lifespan

APPLICATIONS

- For use with compatible Constant Voltage 12V DC LED lighting. Not for use with dimmers.

Wattage	Order SKUs
12 Watts	EL-PNP-12W-12V
24 Watts	EL-PNP-24W-12V
36 Watts	EL-PNP-36W-12V

