

SPECIFICATION SHEET

JOB NAME: _____

LOCATION: _____

QUOTE/REF#: _____



SPECIFICATIONS

- Input Voltage:** 12 or 24V DC
- Output Channels:** 1
- Input:** 2 Wire (Positive + / Negative -)
- Output:** 2 Wire (Positive + / Negative -)
- Max Load:** 8 amp, 72 Watts (12V DC), 144 Watts (24V DC),
- Working Temp:** -20 to 60 °C
- Environment:** Dry Location
- IP Rating:** IP20
- Controller Size:** 3.5 in. L x 2.3 in. W x 1.37 in. H
89 mm L x 59 mm W x 35 mm H
- Warranty:** 1 Year Limited

DESCRIPTION

The LED Rotary Knob Dimmer Switch is used for our 12 or 24V LED lighting. It features high quality and 100% brightness adjustable dimming. They are easy to install and adjust the lighting smoothly without any flickering.

KEY FEATURES

- High freq. pulse dimming ensures no flicker (~690 Hz)
- Easy to Install and Use
- ~8 Amp peak max load
- 12V or 24V DC max output to protect LEDs
- Input and output screw-down terminal block connections
- Screw tabs for easy mounting

APPLICATIONS

- Trade Show & Exhibit Lighting
- Retail Display Lighting
- Architectural Lighting
- Hotels, Casinos, and Clubs
- Custom Lighting Shows
- Stage Lighting

