



HUSQVARNA G1300P

Small, compact, durable generator with 0.8kW (50Hz) output for efficient powering of homes and work sites. 6L fuel tank for tough, reliable performance from its easy-start petrol engine in all conditions. Ergonomic design allows easy portability, while a user-friendly dashboard means easy usability, even in emergencies.



External fuel cap for easy refueling

External fuel cap for easy refueling



Visible fuel level

Transparent fuel indicator makes it easy to check fuel level.

FEATURES

- Visible fuel level
- External fuel cap for easy refueling

Technical Specifications

CAPACITY

Horsepower	1.1 hp
Power	800 W

DIMENSIONS

Article gross weight	29200 g
Article net weight	28000 g
Weight	28 kg

EMISSION DATA

Exhaust emissions (CO2 EU V)	603 g/kWh
------------------------------	-----------

ENGINE

Cylinder displacement	98.5 cm ³
Motor/engine manufacturer	Weima

EQUIPMENT

Air filter type	Dry
Starter	Recoil
Technical Platform	Generators EMM

LUBRICANTS

Engine oil capacity (L)	0.45
Engine oil type	SAE 10W-30
Fuel consumption	395 g/kWh
Fuel tank volume (with reserve)	6 l

MATERIALS

Master pack: Paper + Cardboard	0 g
Metal total	0 g
Paper + Cardboard total	0 g
PE total	0 g
PET total	0 g
Plastic foil	0 g
Plastic rigid	0 g
Plastic total	0 g
PS/EPS/HIPS total	0 g

PACKAGING

Packaging height	415 mm
Packaging length	485 mm
Packaging volume	75.48 dm ³
Packaging width	375 mm
Quantity in Master pack	1