

PROJECT NAME	
ORDERING #	TYPE



DETAILS

With easy-swap end caps, this double-ended ballast-bypass 8ft LED tube is compatible with both FA8 and R17D sockets in T8 and T12 fixtures. The tube light features a long-lasting quality build, 4,300-lumen output, and >83 CRI. Upgrade your 8ft fluorescent fixtures today and enjoy energy & maintenance savings with our Type B 8ft LED Tube for years to come.

SPECIFICATIONS

Input Power	36W
Input Voltage	120-277VAC
Light Output	4,300 lumens
System Efficacy	119 lm/W
CCT	5000K
CRI	>83
Average Lamp Life	50,000 hours
Base Type	FA8 (Standard) R17D (Optional Accessory)
Cover	Frosted or Clear
Housing	Aluminum & polycarbonate
Beam Angle	140°
Tube Length	8'
Certification	DLC 5.1, UL
Warranty	5 years



FA8



R17D

ORDERING

Example: **8FTFA836WPV50C**

SKU Root	Wattage / Lumens	PV	CCT	Finish
8FTFA8	36W - 36W, 4,300 lumens	PV	50 - 5000K	C - Clear F - Frosted

ACCESSORIES

Item Type	SKU	Description	Image
End Cap	ACCXPVR17DENDCAP	R17D End Cap for End-Cap-Swappable 8ft Tubes	