



**HIVE™**

# HIVE 318MHz GDO Receiver

Stand Alone - DIP Switch Receiver



## FEATURES

- 1-Channel
- Tan
- Includes Coax Antenna & Wiring Harness
- 12-24 VAC/DC
- Compatible with Allstar DIP Switch and Classic transmitters



## SPECIFICATIONS

Output Load Max:	15A/125AC
Input Load:	12-24VACDC
Power Consumption:	32mA/70mA
Max Applicable Power:	25VDC
Operating temperature:	-40F - 158F
Dimensions:	3W x 3 1/2L x 1 1/4D

## ACCESSORIES

- Stinger 318MHz
- Firefly 318MHz



\* Compatible with Allstar DIP switch and Classic transmitters



PIERCE BUILDING: 3788 WEST 2270 SOUTH, SUITE E  
 SALT LAKE CITY, UT 84120  
 (866) 975-0101 • (866) 975-0404 FAX  
 WWW.TRANSMITTERSOLUTIONS.COM

All items are trademarks of their respective holders.

To have your fax number removed from future specials, please call Removal Services - 800-915-2571 ext. 47540 or fax to 866-975-0404.