

# SMART-IN

Code: SP1000, SP1000-i



**SP1000**



**SP1000-i**

| Smart-in pure                            | SP 1000                | SP 1000-i              |
|------------------------------------------|------------------------|------------------------|
| Continuous output power                  | 1000W                  | 1000W                  |
| Peak output power                        | 2500W (pochi secondi)  | 2500W (pochi secondi)  |
| Output voltage(RMS)/Freq.                | 230VAC/50Hz $\pm$ 3 Hz | 230VAC/50Hz $\pm$ 3 Hz |
| Usb output                               | 5V @ 2.1A              | 5V @ 2.1A              |
| Input voltage                            | 12V / 490 ma           | 12V / 490 ma           |
| Swith time from battery to main AC line. | /                      | 20ms                   |
| Switch time from main line to battery    | /                      | 100ms                  |
| Input voltage                            | 12V                    | 12V                    |
| Dimensions [mm]                          | 262,4 x 270 x 107,5    | 262,4 x 270 x 121      |