




6. **Secure the Wall Anchor A.** Place the **Wall Anchor A** in the orientation shown and screw the **M5 X40 screws** halfway with the **Phillips screwdriver**. Use level to ensure the anchor is straight, then tighten the screws completely with the **Phillips screwdriver**.




7. **Secure the Circolo Anchor B.** Gently place the CIRCOLO facedown on a **blanket**. Place the **CIRCOLO Anchor B** in the orientation shown and screw the **M4 X8 screws** with the **Phillips screwdriver**.



8. **Insert power cord and hang the CIRCOLO.** Insert the power cord into the CIRCOLO and put down the snap. Lift the **CIRCOLO Anchor B** over the **Wall Anchor A**. Adjust the CIRCOLO horizontally as necessary and ensure the placement is secure. Plug the power cord into an outlet.




9. **Clean and test.** Turn on the power switch located in the left of the bottom of CIRCOLO. Follow on screen instructions to finish WIFI setup. Tear off the CIRCOLO's protective film, wipe the mirror off clean with the **wiping cloth** provided, and start your fitness journey.




4

MASONRY/DRYWALL INSTALLATION GUIDANCE


1. **Mark the horizontal reference line.** Use a tape measure to mark the wall at a height of approximately 51" from the floor. Use the **level** and **pencil** to draw a horizontal reference line at the mark.




2. **Mark pilot holes.** Align the upper edge of the **Wall Anchor A** and the reference horizontal line, Hold the **Wall Anchor A** by hand, use a **pencil** to mark the location in the two holes respectively. Which we denoted as X1 and X2.



3. **Drill pilot holes.** Use a drill and 5/16" drill bit to make holes in X1 and X2 respectively. Each hole should be drilled 1-3/4" deep. Make sure the holes are perpendicular to the wall. If not, need to start again along the horizontal reference line.




4. **Set the anchors.** Align the **M8x40 Anchors** so that they are perpendicular to the wall, then **hammer** them in gently one at a time until each one is flush with the wall.




5


5. **Secure the Wall Anchor A.** Place the **Wall Anchor A** in the orientation shown and screw the **M5 X40 screws** halfway with the **Phillips screwdriver**. Use level to ensure the anchor is straight, then tighten the screws completely with the **Phillips screwdriver**.




6. **Secure the Circolo Anchor B.** Gently place the CIRCOLO facedown on a **blanket**. Place the **CIRCOLO Anchor B** in the orientation shown and screw the **M4 X8 screws** with the **Phillips screwdriver**.



7. **Insert power cord and hang the CIRCOLO.** Insert the power cord into the CIRCOLO and put down the snap. Lift the **CIRCOLO anchor B** over the **Wall Anchor A**. Adjust the CIRCOLO horizontally as necessary and ensure the placement is secure. Plug the power cord into an outlet.



8. **Clean and test.** Turn on the power switch located in the left of the bottom of CIRCOLO. Follow on screen instructions to finish WIFI setup. Tear off the CIRCOLO's protective film, wipe the mirror off clean with the **wiping cloth** provided, and start your fitness journey.



6

Thank you for choosing CIRCOLO fitness mirror.

Please read this manual carefully before use.

Have a great experience!

NOTICES








- Do not place the device in a location where it can be easily exposed to water.
- Please keep the device away from heat source and high temperature environment.
- When handling the device, please put the mirror side upwards to prevent the machine from falling.
- Please use the wiping cloth, installation components and power cord provide by CIRCOLO.
- This product is only allowed to clean the mirror by the wiping cloth with a little water, not using alcohol and other corrosive solutions.
- To avoid the risk of electric shock, please do not disassemble the machine by yourself.
- This product is not to be used by children alone, children must be accompanied by adults to use.
- By using this product, you acknowledge you agree to the CIRCOLO Terms of Service (<https://assets.circolo.us/about/terms-of-service.html>) and Privacy Policy (<https://assets.circolo.us/about/privacy-policy.html>). Customer service hotline : +1(415)579-0299

PRODUCT PACKING LIST










1 CIRCOLO Fitness Mirror	1 Product Manual
1 Wiping Cloth	1 Installation Components
1 Power Cord	1 Therapy band
2 Mini loop band	1 Long power loop band

INSTALLATION PREPARATION

Installation Components


1 Wall Anchor - A	
1 CIRCOLO Anchor - B	
2 M4x8 Screws	
2 M8x40 Anchors	
2 M5x40 Screws	

Necessary tools

1 Drill	
1 5/16" Drill Bit	
1 Hammer	
1 Level	
1 Phillips Screwdriver	
1 Pencil	
1 Stud Finder	
1 Tape Measure	
1 Blanket	


STUD INSTALLATION GUIDANCE

1. **Locate stud.** Select a location for the CIRCOLO within 4' of an outlet. Using the **stud finder**, find one stud to which you want to attach the wall mount. At approximately 51" height from the floor, mark the left & right side of it with **pencil**, then determine the stud's center & mark vertically.




2


2. **Mark the horizontal reference line.** Use a tape measure to mark the wall at a height of approximately 51" from the floor. Use the **level** and **pencil** to draw a horizontal reference line at the mark. The intersection of the reference horizontal line and the stud center vertical line in the first step is denoted as point A.




3. **Mark pilot holes.** Align the upper edge of the **Wall Anchor A** and the reference horizontal line, and center at point A, Hold the **Wall Anchor A** by hand, use a **pencil** to mark the location in the two holes respectively, which we denoted as X1 and X2.



4. **Drill pilot holes.** Use a **drill** and **5/16" drill bit** to make holes in X1 and X2 respectively. Each hole should be drilled 1-3/4" deep. Make sure the holes are perpendicular to the wall. If not, need to start again along the horizontal reference line;



5. **Set the anchors.** Align the **M8x40 Anchors** so that they are perpendicular to the wall, then **hammer** them in gently one at a time until each one is flush with the wall.



3