

Socket Tester Automatic Electric Circuit

HT107E



- 1. Design with RCD / GFCI Test Button
- 2. Bright LED Light & 3 Test Indicators
- 3. easy to judge

1. General Specifications

This socket tester rapidly detect whether the socket's wire connection is correct or not. With several indicators to indicate the state of the socket, also with LCD voltage display. It is used to detect whether neutral, live and earth wire is connected correctly and to indicate which wire is missing.

2. Technical Specifications

Voltage Measurement	90~250V / 45~65Hz
Phase Voltage	90~250V / 45~65Hz
Leakage Voltage	0~99V / 45~65Hz
Accuracy	±(2.0%+2)
RCD Test	> 30mA
RCD Working Voltage	220V ± 20V
GFCI Test	>5mA
GFCI Working Voltage	110V±20V
Material	Flame Retardant ABS
Plug Type	UK
Working Environment	
TTOTKING ETTITIOTITIOTIC	0-40°C, 20% ∼75%RH
Storage Environment	0-40°C, 20% ~75%RH -10~50°C, 20% ~80%RH
· ·	
Storage Environment	-10~50°C, 20% ~80%RH EN61010-1,-2-030, EN61326-1,
Storage Environment Safety Rating	-10~50°C, 20% ~80%RH EN61010-1,-2-030, EN61326-1, CAT II 300V

