

# 30 Series Trims

## 30 Series Exit Device

The trim function determines the function of the exit device. All 28 Series trims work with all 30 Series Exit Devices, except where noted.  
**Note:** All trims and exit devices are ordered and packaged separately.

### 28 Series Lever & Rose Trim for 3727/3828 Series Exit Devices




**Lever & Rose Trim**

- For 1-3/4" (44mm) doors only
- Functions available for 04, 06, 10, 13 & 15
- Not handed
- Finishes: 03, 04, 10, 10B, 10BE, 20D, 26D, BSP & WSP
- Lever designs available: "L", "B", "P"

To order specify 28 followed by the function  
Trim will not retrofit on devices purchased prior to 2000. Consult factory.

(K, N, D, C or L), the rose (L), the lever (L, B or P) and finish


Example: 28-K-LL x 26D



**28-K-LL  
Night Latch**

Key in lever retracts latchbolt.


**04 Function  
For 3828 only  
(ANSI 03)**



**28-N-LL  
Night Latch**

Lever operates only when key is in cylinder and turned.


**06 Function  
(ANSI 09)**



**28-D-LL  
Dummy**

Lever rigid at all times & no outside function.


**10 Function  
(ANSI 02)**



**28-C-LL  
Entrance**

Key in lever locks or unlocks lever.

**13 Function  
(ANSI 08)**



**28-L-LL  
Passage**

Latchbolt operated by lever.

**No Cylinder  
15 Function  
(ANSI 14)**

### 28 Series GTB/HTB Pulls & Plates for 3727/3828 Series Exit Devices



810-GTB



802-GTB




814-HTB

- For 1-3/4" (44mm) doors standard
- Through-bolted with 3 mortise nuts
- Pulls project 1-1/2" (38mm) from door face
- GTB Design trim will cover a 161 cutout
- Trim ordered separately.
- Finishes: EN, EB, ED, EP & EAB

• For cylinder operation only with no trim (Specify 3828 x 34 rim cylinder x Finish)

To order specify: trim design and finish


Example: 814-HTB x EN



**814-HTB  
Night Latch**

Outside by pull and key. (3828 only)


**04 Function  
(ANSI 03)**



**810-GTB  
Exit Only with Pull**

Outside pull when push bar is locked down.

**10 Function  
(ANSI 02)**



**802-GTB  
Exit Only**

Blank plate to cover 161 cutout.

**10 Function  
(ANSI 01)**

### 28 Series Thumbpiece Trim for 3727/3828 Series Exit Devices



- Finishes: EN, EB, ED, EP & EAB
- \*1 3/4" Door Only


### 28 Series OB Knob Trim for 3727/3828 Series Exit Devices



- For 1-3/4" (44mm) doors only
- Functions available for 04, 13 and 15
- Non-handed
- Finishes: 03, 04, 10, 10B, 10BE, 20D, 26D, BSP & WSP

To order specify 28 followed by the function (K, C or L), the rose (O), the knob (B) and finish


Example: 28-K-OB x 26D



**28-K-OB  
Night Latch**

Key in knob retracts latchbolt.


**3828 only  
04 Function  
(ANSI 03)**



**28-C-OB  
Entrance**

Key in knob locks or unlocks knob.

**13 Function  
(ANSI 08)**



**28-L-OB  
Passage**

Latchbolts operated by knob.

**No Cylinder  
15 Function  
(ANSI 14)**

**866-TP**  
Key locks or unlocks thumbpiece. (63)

**814-TP**  
Key retracts latchbolt. (3828 ONLY) (04)

**828-TP**  
Thumbpiece always operable. (28)

**810-TP**  
Dummy trim. (10)

To order specify: trim design and finish  
Example: 866-TP x EN