
DIMENSION® LED Tape Light Kits


64-162 L-Shaped Tape-to-Tape Connector Installation


Quick Reference Guide on how to line-up and install 2 pieces of LED Tape Light using the 64-162 L-Shaped Tape-to-Tape Connector.



* - There should be no power to the LED Tape Light through this process.







Prior to installation, make sure the tape is cut at the copper indicators. The markings of the tape must match up.

24VDC+ is Power W is White WW is Warm White B is Blue R is Red G is Green 24VDC+ should line up to 24VDC+. W should line up to W. And so forth. Make sure the connector is lined so the connector pins press down into the copper indicators on both ends. Use pliers, or another tool, to secure each end of the connector.

