



Battery Cabinet

TOWER TYPE

MODEL	Battery Quantity						Weight(Kgs)	Cabinet Dimension (CM)		
	12AH	17AH	26AH	40AH	65AH	100AH	N.W	Length	Width	Height
X1/C1	4	5	2	2	1	1	3.8	43.5	21	29
X2/C2	8	10	4	4	2	2	5.8	45	47	32
X3/C3	12	14	6	6	3	3	8	58.5	43	32
X4/C4	16	20	8	8	4	4	18.5	45	47	61.5
X6/C6	20	24	12	12	6	6	21	58.5	47	61.5
X8/C8	28	36	16	16	8	8	23	78	47	61.5
X10/C10	36	44	20	20	10	10	26	95	47	61.5
X12/C12	42	54	24	24	12	12	31	78	47	90
X16/C16	56	72	32	32	16	16	42	78	49	119
X20/C20	-	-	40	40	20	20	53.5	95	47	119
X32/C32	-	-	62	62	32	32	66.5	78	88	119

Product specifications are subject to change without further notice.

RACK TYPE

MODEL	Battery Quantity			Weight(Kgs) (Without Battery)	Cabinet Dimension (CM)		
	7AH	9AH	10AH	N.W	Length	Width	Height
G4R	4	4	4	6.1	38	43.8	8.8
G6R	6	6	6	9.1	48	43.8	8.8
G8R	8	8	8	9.1	48	43.8	8.8
G12R	12	12	12	11.3	60	43.8	8.8
G16R	16	16	16	12.5	60	43.8	13.3
G20R	20	20	20	12.5	60	43.8	13.3

Product specifications are subject to change without further notice.



19" Rack Type Cabinets

X Series / C Series Cabinets

Ver1.0_20.02.2024

Authorised Distributor/ Reseller:

Compatible with:



Windows



macOS



Linux

Prolink is a registered trademark of Fida International (S) Pte Ltd. Other brands and product names are trademarks or registered trademarks of their respective holders. Product images are purely for illustrative purposes and may defer from the actual product. Specifications are subjected to changes without prior notice. Copyright © 2024 Fida International (S) Pte Ltd.