LED Multi Pendant



START FROM HERE

- Make sure **POWER** is **COMPLETELY OFF** at the fuse box
- Have your fixture installed by a qualified licensed electrician
- Prepare everything in a clear area
- · Wear gloves at all time during this installation
- · Read instructions carefully before you start assembly
- Keep this installation sheet for future reference

Technical Support: 1-855-855-8926

Please Note:

- All Kuzco LED fixture comes with pre-wired LED module(s).
- Unless instructed to do so, please do not touch any part of the LED module(s) as any unnecessary contact with the module could cause permanent damage.
- For dimming, an ELV (Electronic Low Voltage) or TRIAC type of dimmer is required.
- 120V input

- 1. Remove the fixture from it's original packaging
- 2. Separate the mounting plate (1c) from within the canopy (2a) by removing the canopy screws (2b)
- Attach mounting plate (1c) to electrical junction box (1a) using screws provided (1e) in hardware package
- 4. Secure mounting plate (1c) to mounting surface with anchors (1f) and screws (1g)
- **5.** To change fixture height, push and hold wire gripper (2g), slide wire to desired length and then release wire gripper (2g) to secure
- **6.** Make proper electrical connections (black to hot "L", white to neutral "N", ground to "GND") with wire nuts **(1b)** provided in hardware package
- Secure canopy (2a) to mounting plate (1c) with canopy screws (2b)
- **8.** Connect fixture (2d) to fixture hub (2c)
- **9.** Fine tone wire length if necessary, by push and hold wire gripper (2g) and then adjust wire to desired length



