# **Angelo Pendant**

### GENERATION LIGHTING

#### **Pendant**

#### **GENERAL PRODUCT INFORMATION:**

These fixtures are intended to be installed utilizing NEC compliant junction boxes.


This product is safety listed for damp locations.

Incandescent lamps may be dimmed with a standard incandescent dimmer. LED lamps may be dimmed with a LED dimmer. Consult lamp manufacturer for additional information.

#### **CAUTION - RISK OF FIRE**

This product must be installed in accordance with the applicable installation code by a person familiar with the construction and operation of the product and the hazards involved.

Use minimum 90°c supply conductors.



- If necessary, screw the short end of the threaded nipple tightly onto the mounting plate.
- 2 Screw the lamp into the socket. Refer to the label for Max Wattage Information.
- Remove the bottom frame and cover by removing the frame screws.
- Insert the glass into the fixture frame, place the bottom cover on the bottom frame, and secure the bottom frame to the fixture frame using the frame screws.
- Determine the wanted height or look of the fixture with the provided stems and pivot, then assemble them by screwing them together.
- Feed the fixture wires through the stem assembly and screw it onto the socket assembly.
- 7 Unscrew the collar nut off the screw collar and place it onto the stem followed by the canopy.
- 8 Screw the screw collar onto the threaded nipple.
- 9 Feed the fixture wires through the threaded nipple and screw the mounting plate assembly onto the stem assembly.
- 10 Align and secure the mounting plate to the junction box.
- Connect the fixture to a suitable ground in accordance to local electrical codes.
- Connect the white fixture wire (square and/or rigid) to the neutral power line wire with a wire nut.
- Connect the black fixture wire (round and/or smooth) to the hot power line wire with a wire nut.
- Neatly place all the wires into the junction box, place the canopy onto the mounting plate, and secure it in place by screwing the collar nut tightly onto the screw collar.

## **SAVETHESE INSTRUCTIONS!**

GENERATION LIGHTING

7400 Linder Ave, Skokie, IL 160077 800.969.3347

### www.generationlighting.com

© 2019 Generation Lighting. All rights reserved.

The "Generation Lighting" graphic is a registered trademark of Generation Lighting. Generation Lighting reserves the right to change specifications for product improvements without notification.