

LEO SWITCHED

astro

GENERAL

| | |
|---------------------------|---|
| LOCATION: | Interior |
| CLASS: | cULus (Class 1) |
| LOCATION RATING: | Dry |
| DRIVER REQUIRED: | Mains 120V |
| INSTALLATION ORIENTATION: | Wall Mount - Horizontal Wall Mount - Vertical |
| FITTING METHOD: | Included Junction Box |
| MAIN MATERIAL: | Metal - Brass |
| DIMENSIONS (mm): | H:120 W: 45 D: 92 |
| DIMENSIONS (inch): | H: 4.72 W:1.77 D: 3.62 |
| CUT OUT HOLE (mm/inch): | H:4.33" W:1.38" |
| RECESS DEPTH (mm/inch): | 90mm/3.54" |
| FIRE RATING: | - |
| CABLE LENGTH (mm/inch): | - |
| GROSS WEIGHT (lb): | 2.64 |
| ADA COMPLIANT: | Yes - if installed in compliance with ADA 307.2, 308, 309.3, 309.4 |
| IC RATING: | IC Rated |

LAMP

| | |
|--------------------------------|----------------|
| LIGHT SOURCE: | High Power LED |
| WATTAGE: | 2W |
| LAMP INCLUDED: | Yes (Integral) |
| MAXIMUM LAMP LENGTH (mm/inch): | - |
| LUMINOUS FLUX (lm): | 99 |
| COLOUR TEMP (K): | 2700 |
| CRI (Ra): | 90 |
| MACADAM ELLIPSE: | 3-Step |
| TILT ADJUSTABLE ANGLE (°): | - |
| ROTATION ADJUSTABLE ANGLE (°): | - |
| LIFETIME (hrs): | L70 60000 |
| BEAM ANGLE (°): | 18.1 |

ELECTRICAL

| | |
|-----------------------------|---------|
| SWITCHED: | Yes |
| DIMMABLE: | - |
| DIMMING METHOD: | - |
| SUPPLY FREQUENCY (Hz): | 50/60 |
| DRIVER/BALLAST VOLTAGE (V): | 100-240 |
| DRIVER LIFETIME (hrs): | 60000 |
| EFFICACY (lm/W): | 34.17 |

ADDITIONAL INFORMATION

| | |
|-----------------|---|
| SHADE INCLUDED: | - |
| SHADE MATERIAL: | - |
| F MARK: | Not suitable for mounting in flammable materials |



CODE: 1295009
FINISH: POLISHED CHROME



CODE: 1295010
FINISH: MATT NICKEL



CODE: 1295011
FINISH: BRONZE

TO MAINTAIN THIS PRODUCT TO ITS BEST CONDITION, PLEASE VIEW OUR CARE AND CLEANING GUIDE ON THE SUPPORT SECTION OF THE ASTRO WEBSITE.

Pour entretenir au mieux ce produit, veuillez consulter notre guide d'entretien et de nettoyage, dans la rubrique d'aide sur le site Web d'Astro.

Um dieses Produkt im besten Zustand zu erhalten, beachten Sie bitte unseren Leitfaden zu Pflege und Reinigung im Abschnitt „Support“ auf der Astro-Website.

Per mantenere questo prodotto nelle sue migliori condizioni, consultare la nostra guida per la manutenzione e la pulizia nella sezione dedicata all'assistenza del sito Web Astro.

PRODUCT ELEVATIONS

astro

Please note that some dimensions may vary slightly due to manufacturing tolerances, this includes cable entry and fixing holes.

