

- Single or Dual Action
- Break Glass
- Lift and Pull
- Terminal strip or Pigtail connection
- 9 different colors
- Custom lettering available in any language
- · Single or Double contact
- ULC listed and FM Approved

RMS Series

Fire alarm pull stations

Tomar manual pull stations are made entirely in the U.S.A. of the finest materials and workmanship available. The low profile design and smooth edges offer an attractive yet functional design. They are constructed of highstrength metal die-cast alloy, and will operate equally well in commercial, municipal, and industrial environments.

Tomar Single Action manual pull stations are activated quickly and easily by pulling down the T-handle. Dual Action Lift and Pull and Break Glass are available to minimize accidental or malicious alarm activations.

Electrically the Tomar pull station is unbeatable with 10 amp snap action switch offered in all possible contact arrangements (including gold contacts). Tomar pull stations can be used with or without the included glass rod, with replacement requiring no special tools.

RMS & BREAK GLASS COVER

RMS Ordering Information

Model	Description
RMS-1P	S.P.S.T. with Pigtail connection
RMS-2P	D.P.S.T. with Pigtail connection
RMS-1T	S.P.S.T. with Terminal connection
RMS-2T	D.P.S.T. with Terminal connection
RMS-6T	D.P.D.T. with Terminal connection

Options - please add at time of order

/KL Key lock plus keys

/Color option - Please specify color if other than Red

Accessories

GR Replacement glass rods

BB Indoor back box, surface mount
DBB Deep indoor back box, surface mount

GP Replacement glass LP Lift and Pull cover DAH Break glass adapter

How to Order:

- · Specify model number
- · Specify options, special lettering, and color if other than Red

Architect and Engineer Specifications

The manual pull station shall be Tomar series RMS or approved equal. The pull station shall be ULC listed, and made of high-strength metal die-cast alloy. Single action model activation shall be by T-handle pull-down function. Dual action model activation shall be by Lift and Pull cover, or Break Glass action. The pull station must be able to be activated either with or without a glass rod, which must be field-replaceable and requiring no special tools. The pull station must be available with either single or double pole switch, and with either pigtail or terminal block design.

- Deters vandalism
- Key lock option
- · Mounts readily to wall
- Automatically expels glass when broken
- Heavy gauge steel construction (14 gage)
- Available in red, blue, green, yellow, white, black, gray, purple, and orange

Specifications

Item	Description		
Dimensions	Width -6.6in Height - 7.375in Depth - 2.25in)		
Weight	1.42 lb		
Available Colors	Red, Blue, Green, Yellow, White, Black, Gray, Purple, Orange		

Specifications

Item	Description
Contact Rating	10 amps @ 125/250 VAC.
Contacts	S.P.S.T. (single pole single throw) D.P.S.T. (double pole single throw) D.P.S.T. (double pole double throw)
Operating Temperature	-35° C to 65° C
Wire AWG	12 to 22 AWG
Wiring	Terminal block or pigtail
Construction	Metal
Mounting	Hardware & instructions included
Dimensions Single Action	Width - 3.2in Height - 4.75in Depth875in Weight - 1.0 lb
Dimensions Dual Action, Lift and Pull (LP)	Width - 3.2in Height - 4.75in Depth - 1.5in Weight - 1.2 lb
Dimensions Dual Action, Break Glass (DAH)	Width - 3.2in Height - 4.75in Depth - 1.625in Weight - 1.6 lb
Available Colors	Red, Blue, Green, Yellow, White, Black, Gray, Purple, Orange

Break Glass Cover

This oversize cover for the RMS Series pull stations is made of heavy gage steel and offers the user the proven glass break deterrent. Two unique features include a glass slot which expels glass through the bottom, minimizing possible injury when activating the device. Optionally, the Break Glass Cover offers key-lock access allowing quick and convenient testing without removing screws or fasteners.

The Break Glass Cover mounts readily between device and wall without having to remove wires.

Ordering Information

Model	Description
NC-BGC	Oversize Break Glass Cover
NGC	Replacement Glass