

3 × 8A DMX DECODER AND RGB CONTROL



CODE

BL-PC-LT300

FUNCTION

- Standalone or DMX control for single colour, Tuneable white, and RGB LED ribbon strip
- Can adjust brightness, colour, and speed of lighting
- RF remote included

| OUTPUT CURRENT | MAX. LOADING | VOLTS |
|-----------------------|--------------|--------|
| 3 × 8A channels (24A) | 288W | 12V DC |
| | 576W | 24V DC |

| DIMENSIONS | Controller W128 × L163 × H40mm Remote W50 × L108 × H15mm |
|------------|---|
|------------|---|

| OPERATING TEMP. | -30°C ~ +65°C |
|-----------------|---------------|
|-----------------|---------------|

| HOUSING | Aluminium |
|---------|-----------|
|---------|-----------|

| INGRESS PROTECTION | Indoor use only |
|--------------------|-----------------|
|--------------------|-----------------|

| MOUNTING | 4 × mounting tabs |
|----------|-------------------|
|----------|-------------------|

| CONNECTION METHOD | RJ45, XLR-3, phoenix screw terminals |
|-------------------|--------------------------------------|
|-------------------|--------------------------------------|

| WARRANTY | 5 years |
|----------|---------|
|----------|---------|

| CONTROL | DMX 512 signal |
|---------|----------------|
|---------|----------------|

| COMPLIANCE |  |
|------------|---|
|------------|---|

| MAX. DISTANCE FROM POWER SUPPLY | Recommended under 10 metres For specific projects contact Bright Light |
|---------------------------------|---|
|---------------------------------|---|