



4 × 5A UNIVERSAL CONTROLLER RF + WIFI + VOICE





FUNCTION

- Universal control unit for constant voltage LED Strip 12-24V DC
- Control RGBW, RGB, CCT and single colour
- RF, wired and OneSmart WiFi control
- Frequency of 433.92 MHz

OUTPUT CURRENT	MAX. LOADING	VOLTS
4 × 5A channel	120W	12V DC
(10A max. total)	240W	24V DC

DIMENSIONS	W80 × L80 × H16mm
HOUSING	PVC casing
MOUNTING	Screw fix
WARRANTY	5 years
COMPLIANCE	▲

	OPERATINGTEMP.	-20°C ~ +55°C
	INGRESS PROTECTION	Indoor use only
	CONNECTION METHOD	Concealed screw terminals
	CONTROL	RF, wired inputs and WiFi (OneSmart App)
	FREQUENCY	433.92 MHz (RF) 2.4GHz (WiFi)

CHECK OUT INSTALLATION TUTORIAL VIDEO www.youtube.com/watch?v=_y5ufj6bAhg

ONESMART APP CONTROL





OneSmart is the app for controlling lights and devices from anywhere in the world. It's possible to manage up to 50 installations in different locations and up to 1000 devices for each installation.

OneSmart is compatible with Google home and Amazon Alexa, easy set-up and integration with other home automation devices for commands by voice and Smartphone







Google HOME

MADE IN ITALY

App Store

Google play