

4 × 8A REMOTE RECEIVER



CODE
BL-PC-TOP-V8/4

FUNCTION

- For wireless and wired control of single colour constant voltage LEDs
- On/off; dimmer intensity
- Wide-ranging and accurate dimmer function; fade on and off that can be set to between 0 and 10 seconds
- Frequency of 433.92 MHz

OUTPUT CURRENT	MAX. LOADING	VOLTS
	288W	12V DC
4 × 8A channel (24A max. total)	576W	24V DC
	864W	36V DC

DIMENSIONS	W46 × L174 × H35mm
HOUSING	PVC casing
MOUNTING	Screw fix
WARRANTY	5 years
COMPLIANCE	

OPERATING TEMP.	-20°C ~ +55°C
INGRESS PROTECTION	Indoor use only
CONNECTION METHOD	Concealed screw terminals
CONTROL	RF and wired inputs
FREQUENCY	433.92 MHz

CONNECTIONS

