BRIO[®]Quick Start Guide

BEFORE FIRST USE:

• Some shifting may happen during shipping, so after removing Brio from the packaging, open the rear panel door to check that components are fully pushed into the unit. Replace the panel door.

•Read the Important Safety Information in the Brio User Guide (pages 6-7).

TO OPERATE:

 Place Brio in the selected location and plug the power cord into an electrical outlet.

2. Press the Power button on the Control Panel to start Brio.

3. Press the Power button to change the fan speed or to turn the power off.

The fan speed will be indicated by Control Panel lights. When the power is off, all fan-speed indicator lights on the Control Panel will be off.



Control Panel Display



That's it! Your new Brio Air Purifier is now improving your indoor air quality, trapping and removing airborne particles and pollutants.

Be sure to read the care instructions on the reverse side of this page. Complete instructions can also be found on page 11 of the Brio User Guide.



KEEPING BRIO AT PEAK PERFORMANCE

Brio is designed for home and office use, and in average air quality conditions, Brio's Pre-Filter and Particle Charger should be inspected and cleaned if needed on a monthly basis, following the instructions below.

Brio's powerful fan is designed to draw airborne particles, and it may also draw in settled dust, which can increase the recommended frequency of inspection and cleaning. We recommend that you remove any excess settled dust, debris, or pet hair from the room before Brio is used.

It is normal to hear an occasional snapping or crackling sound, which may mean that a larger piece of dust or debris has collected on the Particle Charger. If you hear frequent snapping sounds, inspect and clean the Pre-Filter and Particle Charger as instructed below. You may also want to check and clean the underside of the APART Case as described below.

How to Inspect and Clean Pre-Filter and Particle Charger

Pre-Filter	Inspect monthly or more often; clean as needed	Remove and inspect the Pre-Filter. Using a soft cloth, remove any visible dust or debris. If extremely dirty, the Pre-Filter can be hand rinsed with water. Air dry completely before use. Re-insert, ensuring it is securely positioned, facing up.
Particle Charger	Inspect monthly or more often; clean as needed	Remove and inspect the Particle Charger. Brush off any visible debris that may have collected there. Next, wipe the wires (both sides) with a damp cloth. This should be done even if it appears clean, as residue may not be visible. Air dry completely before use. Re-insert, ensuring it is securely positioned.
APART Case	Inspect monthly or more often; clean as needed	Remove the APART Case. Dust the metal plate on the bottom of the case with a soft, damp cloth. Air dry completely before use. Re-insert, ensuring it is securely positioned, facing up. Only clean the exterior of the APART case. Do not clean the disposable APART Cartridge.
	brio	More care questions? Visit brioairpurifier.com/care

Visit brioairpurifier.com/care Email: care@brioairpurifier.com