



## PS-AD1000I

Wholesale AC / DC AUTO Converter with isolator

### Features:

- ✧ Input voltage:20~30VAC or 36VDC
- ✧ Output voltage:12VDC
- ✧ Output current: 1A (for IR camera, and long distance transmit)
- ✧ Output short circuit protection
- ✧ Overload protection
- ✧ Auto select 24V AC/12V DC



### Specifications:

Item	AC/DC AUTO Converter
Model Number	PS-AD1000I
Ports	SINGLE
Input Voltage	AC 20V-30V or 36VDC
Output Voltage	DC 12V
Output Current	Nominal 1A
Reset Tim	1 Second
Input Connector	Screw Terminal
Output Connector	Screw Terminal
Operating Conditions	Temperature: -10° C ~ +40° C,
Application	CCTV Camera, IP Camera, PTZ, IR Illuminator, DVR, LED Driver, Access Control , etc.
Size/Net Weight	22*75*30mm / 45g
Package Dimension	26*78*32mm
Certification	CE /RoHS
Carton Weight	QTY/CTN

### Centro Technology Limited

USA Office:15322 E Valley Blvd, City of Industry, CA91746

Phone:(626)391-8868

China Office:4th Floor; Chashu 1#, Area B, HuaFeng 1st Technology, Gushu Sanwei, Xixiang, Shenzhen

Phone:0755-23200933

Website:www.centropower.com

Email:info@centropower.com