



PS-AD1500M

Wholesale AC / DC AUTO Converter

Features:

- ✧ Input voltage:20~30VAC or 36VDC
- ✧ Output voltage:12VDC
- ✧ Output current: 1.5A (for IR camera, and long distance transmit)
- ✧ Output short circuit protection
- ✧ Overload protection



Specifications:

Item	AC/DC AUTO Converter		
Model Number	PS-AD1500M		
Ports	SINGLE		
Input Voltage	AC 20V-30V or 36VDC		
Output Voltage	DC 12V		
Output Current	Nominal 1.5A		
Input Connector	Screw Terminal		
Output Connector	Screw Terminal		
Operating Conditions	Temperature: -10° C ~ +40° C		
Application	CCTV Camera, IP Camera, PTZ, IR Illuminator, DVR,LED Driver, Access Control , etc.		
Size/Net Weight	22*75*30mm / 45g		
Package Dimension	26*78*32mm		
Certification	CE /RoHS		
Carton Dimension	33*29*24CM		
Carton Weight	200 QTY/CTN GW:9.5KG		

Centro Technology Limited

USA Office:15322 E Valley Blvd, City of Industry, CA91746

Phone:(626)391-8868

China Office:4th Floor; Chashu 1#,Area B,HuaFeng 1st Technology,Gushu Sanwei,Xixiang,Shenzhen

Phone:0755-23200933

Website:www.centropower.com

Email:info@centropower.com