Quick Installation Guide for App (Guarding Vision) via Serial Number with Account Registration For Remote Viewing DVR through Mobile Phone (Android/iOS)

Steps:

A. Check if the DVR is online or offline:

- 1. Go to the DVR's Menu -> Configuration -> Network
- 2. Under General, make sure Enable DHCP is checked and that the IPV4 Address is not 192.168.1.64 (192.168.1.64 means the DVR does not have the right IP address or the DVR is offline).
- 3. Go to Platform Access, make sure Enable is checked and the Status is showing "Online".

B. Download and Install AP "Guarding Vision 🙆 " from the Google Play or Apple Store.

C. Register your E-mail Address or Phone Number to get the Verification Code (VCode 1):

- 1. Click Log-in and click Register to register for an account.
- 2. Use your E-mail Address or Mobile Phone to Register.

The following photos will show how to use your E-mail for Registration

③ 品	•	<	Register
Login to find more	User Name/Email Address		Register using your mobile phone number.
You can also add local device	Password		Register using your E-mail Address.
	Register Forgot Password		
	Login		
Guarding Vision Message More			

- 3. Select Region "**USA**" and click **Finish** on the top right-hand side.
- 4. Input your E-mail address and click Next.
- 5. The server will send a **VCode 1** to your e-mail.
- 6. Once you receive the Verification Code (VCode 1), type it in to the APP.

< Region Finish	Cancel Input the E-mail address.	Cancel Input the verification code				
Select your country of region. It cannot be changed USA		Input the verification code you received. The e-mail or SMS may be delayed. If no message is received				
Uzbekistan	Previous Next	please return to the previous step and get the verification code again.				
Vanuatu	-	Verification Code VCode 1				
Venezuela		Previous (59) Next				

1

D. Register Account name and password:

- 1. User Name: Create your own User Name.
- 2. Password: Create your own password.
- 3. Confirm Password: Re-type your password again.
- 4. Click Finish and login to your account.

Cancel Account Settings			
User Name (Letters, numbers, or symbols.)			
Password (Letters, numbers, or symbols.)			
Confirm Password			
USA			
Finish			

E. Add DVR to your account:

- 1. Once you login to your account, click + (1) on the top right-hand side.
- 2. Select "Manual Adding" (2).
- 3. "Adding Type" should be **Guarding Vision Domain** and type in the **DVR's 9-digit Serial No. (3)**. The serial number is on the label at the bottom of DVR or on the DVR box.
- 4. And then click Search Icon (4) on the top right-hand side to search for the DVR.

ê	٢	1→+	<		Add Device	P
			Serial No.: 671127795		4 clic	k to search
		□ □ Scan QR Code 2 □ □ Manual Adding		ng Type	Guarding Vision [Domain >
			MAC Address: A4:14:37:9F:A4:31 Serial	I No.	671127795	\otimes
		Online Device				
			CF 3			
				ual Input	the 9-digit device se	erial number
			I/P: DC12V, 3.33A, Max 40W			
		Online Device	CE 3 Man	ual Input	the 9-digit device se	∍rial nu

- 5. If DVR is online, the DVR's model# and Serial# will pop up after clicking search.
- 6. Click "Add" (5). A window appear and to ask you to input the Verification Code (6) (VCode 2).
- 7. VCode 2 is in the DVR's menu -> Maintenance -> System Info -> Device Info.
- 8. Once you type in the Verification Code (VCode 2), click OK.

< Res	ults	< Results								System Ma
Guardin	g Vision	Please input the device verification code.	Ce & Log In	System Info System Info Log Information Import/Export Upgrade		Camera me /ersion	Record	Narm I		HDD Embedded Ne V3.4.84, Build ABCdef54321
5 HAR314-16(A		6 OK The verification coo DVR's Menu -> Mainte System Info -> Devi	enance ->	stect	Les	Code s tha	(VCo n 10	ode: dig	de 2 2) is gits	I

Numbers.

- 9. The added device will then be listed under the "Adding Completed".
- 10. Click "**<**" (**7**) **back icon** to go back to the Device list. Your DVR should be showing under My Device.
- 11. Click your DVR or Device and a small live view window will show on the bottom right-hand side. Click the window to change it into full screen for live viewing.

Note: The device/DVR can only be added to one account.

Adding Completed			
Alias 7	HAR314-16(67112	27795 💿	
Device Domain Name	671127795	8	
Port Mapping Mode	Manual	>	
Server Port Number			
HTTP Port Number			

User Name

F. How to delete the device from your account:

- 1. Under my device list, select your DVR, hold it, and slide to left.
- 2. Click setting icon (8) and go to the very bottom.
- 3. Click **Delete Device** (9) and then click **OK**. The device will be deleted from your account.

	+	< Settings
S Recent Live View	>	Alarm Notification Disable >
My Device		
Office Slide to left	0	Storage Status >
	▲	Device Version V3.4.84 build 170919• >
Login to find more	8	
Login	•	Image and Video Encryption OFF
		If enabled, your pictures and videos will be protected by the device password. 9
		Device Information >
		Delete Device