

BESANTEK Personal Safety Voltage Detector is designed to alert user that they are approaching live equipment where dangerous voltage is present.

Features:

- Warning proximity of AC voltage (240V~50kV).
- Waterproof.
- Easy-to-wear on body or belt.
- Ultra high bright LED indication.
- High pitch sound indication.
- Test & diagnostic circuitry.
- Friendly priority alert reporting.
- Circuit test function.
- High impact type casing.
- Different alerting sound & light.
- Can be adapted to sunrise (stick).
- Accessories: Instruction manual, battery, strap, strap connector, pocket and belt clip.



BST-HVD7


Technical Specification:

BST-HVD7	
Detection Voltage	240V~50kV
Applicable Frequency	50/60 Hz
Operating Temperature	-15°C to 55°C
Storage Temperature	-20°C to 65°C
Humidity	93%RH at 40°C
Power Source	9V battery x1
Dimensions	115 (L) x 67 (W) x 30 (H) mm
Weight	146g (battery included)

Ordering Information:

- BST-HVD7: Personal Safety Voltage Detector (240V~50kV).

Accessories



Safety Standard:
• EN 61326-1